

Part No. 060463-00, Rev. B  
July 2017

# OmniSwitch AOS Release 8 Specifications Guide

## 8.4.1.R01

Alcatel-Lucent   
Enterprise

[enterprise.alcatel-lucent.com](http://enterprise.alcatel-lucent.com)

**This user guide documents AOS Release 8.4.1.R01 for the  
OmniSwitch 9900, OmniSwitch 6900, OmniSwitch 6860, and OmniSwitch 6865.  
The functionality described in this guide is subject to change without notice.**

**enterprise.alcatel-lucent.com** Alcatel-Lucent and the Alcatel-Lucent Enterprise logo are trademarks of Alcatel-Lucent. To view other trademarks used by affiliated companies of ALE Holding, visit: [enterprise.alcatel-lucent.com/trademarks](http://enterprise.alcatel-lucent.com/trademarks). All other trademarks are the property of their respective owners. The information presented is subject to change without notice. Neither ALE Holding nor any of its affiliates assumes any responsibility for inaccuracies contained herein. (2017)



26801 West Agoura Road  
Calabasas, CA 91301  
(818) 880-3500 FAX (818) 880-3505

**Service & Support Contact Information**

North America: 800-995-2696  
Latin America: 877-919-9526  
EMEA : +800 00200100 (Toll Free) or +1(650)385-2193  
Asia Pacific: +65 6240 8484  
Web: [support.esd.alcatel-lucent.com](http://support.esd.alcatel-lucent.com)  
Email: [ebg\\_global\\_supportcenter@al-enterprise.com](mailto:ebg_global_supportcenter@al-enterprise.com)

# Contents

	<b>About This Guide</b> .....	vii
	Supported Platforms .....	vii
	Who Should Read this Manual? .....	vii
	When Should I Read this Manual? .....	vii
	What is Not in this Manual? .....	vii
	How is the Information Organized? .....	ix
	Documentation Roadmap .....	ix
	Related Documentation .....	xi
	Technical Support .....	xii
<b>Chapter 1</b>	<b>Switch Management Specifications</b> .....	1-1
	In This Chapter .....	1-2
	Getting Started Specifications .....	1-3
	Login Specifications .....	1-3
	File Management Specifications .....	1-4
	CMM Specifications .....	1-4
	USB Flash Drive Specifications .....	1-5
	CLI Specifications .....	1-5
	Configuration File Specifications .....	1-6
	User Database Specifications .....	1-6
	WebView Specifications .....	1-6
	SNMP Specifications .....	1-7
	Web Services Specifications .....	1-8
	OpenFlow Specifications .....	1-9
	Virtual Chassis Specifications .....	1-10
	Automatic Remote Configuration Specifications .....	1-11
	Automatic Fabric Specifications .....	1-11
	NTP Specifications .....	1-11
<b>Chapter 2</b>	<b>Network Configuration Specifications</b> .....	2-1
	In This Chapter .....	2-2

Ethernet Specifications .....	2-3
UDLD Specifications .....	2-3
Source Learning Specifications .....	2-4
VLAN Specifications .....	2-4
High Availability VLANs Specifications .....	2-5
Spanning Tree Specifications .....	2-5
Loopback Detection Specifications .....	2-6
Static Link Aggregation Specifications .....	2-6
Dynamic Link Aggregation Specifications .....	2-6
Dual-Home Link Specifications .....	2-6
ERP Specifications .....	2-8
MVRP Specifications .....	2-8
802.1AB Specifications .....	2-8
SIP Snooping Specifications .....	2-9
IP Specifications .....	2-10
VRF Specifications .....	2-11
IPv6 Specifications .....	2-12
IPsec Specifications .....	2-14
RIP Specifications .....	2-15
BFD Specifications .....	2-15
DHCP Relay Specifications .....	2-16
DHCP Server Specifications .....	2-17
VRRP Specifications .....	2-18
Server Load Balancing Specifications .....	2-18
IPMS Specifications .....	2-19
IPMSv6 Specifications .....	2-20
QoS Specifications .....	2-21
LDAP Policy Server Specifications .....	2-22
Authentication Server Specifications .....	2-22
UNP Specifications .....	2-23
Access Guardian Specifications .....	2-24
AppMon Specifications .....	2-25
Application Fingerprinting Specifications .....	2-25
Port Mapping Specifications .....	2-25
Learned Port Security Specifications .....	2-25

	Port Mirroring Specifications .....	2-27
	Port Monitoring Specifications .....	2-27
	sFlow Specifications .....	2-28
	RMON Specifications .....	2-29
	Switch Health Specifications .....	2-30
	VLAN Stacking Specifications .....	2-31
	Switch Logging Specifications .....	2-32
	Ethernet OAM Specifications .....	2-33
	SAA Specifications .....	2-33
<b>Chapter 3</b>	<b>Advanced Routing Configuration Specifications .....</b>	<b>3-1</b>
	In This Chapter .....	3-1
	OSPF Specifications .....	3-2
	OSPFv3 Specifications .....	3-3
	IS-IS Specifications .....	3-4
	BGP Specifications .....	3-5
	Multicast Boundary Specifications .....	3-6
	DVMRP Specifications .....	3-6
	PIM Specifications .....	3-7
	MBR Specifications .....	3-8
<b>Chapter 4</b>	<b>Data Center Switching Specifications .....</b>	<b>4-1</b>
	In This Chapter .....	4-2
	Data Center Bridging Specifications .....	4-3
	Shortest Path Bridging Specifications .....	4-4
	VXLAN Specifications .....	4-5
	VXLAN Snooping Specifications .....	4-5
	FIP Snooping Specifications .....	4-6
	FCoE/FC Gateway Specifications .....	4-7
	Edge Virtual Bridging Specifications .....	4-8
<b>Appendix A</b>	<b>Software License and Copyright Statements .....</b>	<b>A-1</b>
	ALE USA, Inc. License Agreement .....	A-1
	ALE USA, Inc. SOFTWARE LICENSE AGREEMENT .....	A-1
	Third Party Licenses and Notices .....	A-4
	<b>Index .....</b>	<b>Index-1</b>



# About This Guide

This *OmniSwitch AOS Release 8 Specifications Guide* provides Specification tables for all the OmniSwitch AOS Release 8 Products.

## Supported Platforms

The information in this guide applies only to the following products:

- OmniSwitch 9900 Series
- OmniSwitch 6900 Series
- OmniSwitch 6860 Series
- OmniSwitch 6865 Series

## Who Should Read this Manual?

The audience for this user guide are network administrators and IT support personnel who need to configure, maintain, and monitor switches and routers in a live network.

## When Should I Read this Manual?

Read this guide as soon as you are ready to integrate your OmniSwitch into your network. You should already be familiar with the basics of managing a single OmniSwitch as described in the *OmniSwitch AOS Release 8 Switch Management Guide*.

The information provided in the Specification tables in this guide assume a basic understanding of OmniSwitch administration commands and procedures.

## What is Not in this Manual?

Procedures for switch management methods, such as CLI, web-based (WebView or OmniVista) or SNMP, are outside the scope of this guide.

For information on WebView and SNMP switch management methods consult the *OmniSwitch AOS Release 8 Switch Management Guide*. Information on using WebView and OmniVista can be found in the context-sensitive on-line help available with those network management applications.

This guide is designed to provide feature specification information only and is not intended as a reference for any CLI commands or configuration information. Refer to the Documentation Roadmap for a list of available user guides.



# How is the Information Organized?

Each chapter in this guide corresponds to an OmniSwitch software user manual:

- [Chapter 1, “Switch Management Specifications,”](#) applies to the features described in the *OmniSwitch AOS Release 8 Switch Management Guide*.
- [Chapter 2, “Network Configuration Specifications,”](#) applies to the features described in the *OmniSwitch AOS Release 8 Network Configuration Guide*.
- [Chapter 3, “Advanced Routing Configuration Specifications,”](#) applies to the features described in the *OmniSwitch AOS Release 8 Advanced Routing Configuration Guide*.
- [Chapter 4, “Data Center Switching Specifications,”](#) applies to the features described in the *OmniSwitch AOS Release 8 Data Center Switching Guide*.

## Documentation Roadmap

The OmniSwitch user documentation suite was designed to supply you with information at several critical junctures of the configuration process. The following section outlines a roadmap of the manuals that will help you at each stage of the configuration process. Under each stage, we point you to the manual or manuals that will be most helpful to you.

### Stage 1: Using the Switch for the First Time

**Pertinent Documentation:** *OmniSwitch Hardware Users Guide*  
*Release Notes*

This guide provides all the information you need to get your switch up and running the first time. It provides information on unpacking the switch, rack mounting the switch, installing NI modules, unlocking access control, setting the switch’s IP address, and setting up a password. It also includes succinct overview information on fundamental aspects of the switch, such as hardware LEDs, the software directory structure, CLI conventions, and web-based management.

At this time you should also familiarize yourself with the Release Notes that accompanied your switch. This document includes important information on feature limitations that are not included in other user guides.

### Stage 2: Gaining Familiarity with Basic Switch Functions

**Pertinent Documentation:** *OmniSwitch Hardware Users Guide*  
*OmniSwitch AOS Release 8 Switch Management Guide*

Once you have your switch up and running, you will want to begin investigating basic aspects of its hardware and software. Information about switch hardware is provided in the *Hardware Guide*. This guide provide specifications, illustrations, and descriptions of all hardware components, such as chassis, power supplies, Chassis Management Modules (CMMs), Network Interface (NI) modules, and cooling fans. It also includes steps for common procedures, such as removing and installing switch components.

The *OmniSwitch AOS Release 8 Switch Management Guide* is the primary users guide for the basic software features on a single switch. This guide contains information on the switch directory structure, basic file and directory utilities, switch access security, SNMP, and web-based management. It is recommended that you read this guide before connecting your switch to the network.

## Stage 3: Integrating the Switch Into a Network

**Pertinent Documentation:** *OmniSwitch AOS Release 8 Network Configuration Guide*  
*OmniSwitch AOS Release 8 Advanced Routing Configuration Guide*  
*OmniSwitch AOS Release 8 Data Center Switching Guide*

When you are ready to connect your switch to the network, you will need to learn how the OmniSwitch implements fundamental software features, such as 802.1Q, VLANs, Spanning Tree, and network routing protocols. The *OmniSwitch AOS Release 8 Network Configuration Guide* contains overview information, procedures, and examples on how standard networking technologies are configured on the OmniSwitch.

The *OmniSwitch AOS Release 8 Advanced Routing Configuration Guide* includes configuration information for networks using advanced routing technologies (OSPF and BGP) and multicast routing protocols (DVMRP and PIM-SM).

The *OmniSwitch AOS Release 8 Data Center Switching Guide* includes configuration information for data center networks using virtualization technologies (SPBM, VXLAN, UNP), Data Center Bridging protocols (PFC, ETC, and DCBX), and FCoE/FC gateway functionality.

### Anytime

The *OmniSwitch AOS Release 8 CLI Reference Guide* contains comprehensive information on all CLI commands supported by the switch. This guide includes syntax, default, usage, example, related CLI command, and CLI-to-MIB variable mapping information for all CLI commands supported by the switch. This guide can be consulted anytime during the configuration process to find detailed and specific information on each CLI command.

## Related Documentation

The following are the titles and descriptions of all the related OmniSwitch user manuals:

- *OmniSwitch 9900/6900/6860/6865 Hardware Users Guides*

Describes the hardware and software procedures for getting an OmniSwitch up and running as well as complete technical specifications and procedures for all OmniSwitch chassis, power supplies, fans, and Network Interface (NI) modules.

- *OmniSwitch AOS Release 8 CLI Reference Guide*

Complete reference to all CLI commands supported on the OmniSwitch. Includes syntax definitions, default values, examples, usage guidelines and CLI-to-MIB variable mappings.

- *OmniSwitch AOS Release 8 Switch Management Guide*

Includes procedures for readying an individual switch for integration into a network. Topics include the software directory architecture, image rollback protections, authenticated switch access, managing switch files, system configuration, using SNMP, and using web management software (WebView).

- *OmniSwitch AOS Release 8 Network Configuration Guide*

Includes network configuration procedures and descriptive information on all the major software features and protocols included in the base software package. Chapters cover Layer 2 information (Ethernet and VLAN configuration), Layer 3 information (routing protocols, such as RIP and IPX), security options (authenticated VLANs), Quality of Service (QoS), link aggregation, and server load balancing.

- *OmniSwitch AOS Release 8 Advanced Routing Configuration Guide*

Includes network configuration procedures and descriptive information on all the software features and protocols included in the advanced routing software package. Chapters cover multicast routing (DVMRP and PIM-SM), Open Shortest Path First (OSPF), and Border Gateway Protocol (BGP).

- *OmniSwitch AOS Release 8 Data Center Switching Guide*

Includes an introduction to the OmniSwitch data center switching architecture as well as network configuration procedures and descriptive information on all the software features and protocols that support this architecture. Chapters cover Shortest Path Bridging MAC (SPBM), Data Center Bridging (DCB) protocols, Virtual Network Profile (vNP), and the Edge Virtual Bridging (EVB) protocol.

- *OmniSwitch AOS Release 8 Transceivers Guide*

Includes SFP and XFP transceiver specifications and product compatibility information.

- *OmniSwitch AOS Release 8 Specifications Guide*

Includes Specifications table information for the features documented in the Switch Management Guide, Network Configuration Guide, Advanced Routing Guide, and Data Center Switching Guide.

- Technical Tips, Field Notices

Includes information published by Alcatel-Lucent's Customer Support group.

- *Release Notes*

Includes critical Open Problem Reports, feature exceptions, and other important information on the features supported in the current release and any limitations to their support.

# Technical Support

An Alcatel-Lucent service agreement brings your company the assurance of 7x24 no-excuses technical support. You'll also receive regular software updates to maintain and maximize your Alcatel-Lucent product's features and functionality and on-site hardware replacement through our global network of highly qualified service delivery partners.

With 24-hour access to Alcatel-Lucent's Enterprise Service and Support web page, you'll be able to view and update any case (open or closed) that you have reported to Alcatel-Lucent Enterprise technical support, open a new case or access helpful release notes, technical bulletins, and manuals.

Access additional information on Alcatel-Lucent Enterprise Service Programs:

Web: [support.esd.alcatel-lucent.com](http://support.esd.alcatel-lucent.com)

Phone: 1-800-995-2696

Email: [ebg\\_global\\_supportcenter@al-enterprise.com](mailto:ebg_global_supportcenter@al-enterprise.com)

# 1 Switch Management Specifications

This chapter provides Specifications tables for the following switch management applications and procedures that are used for readying an individual OmniSwitch for integration into a network:

- The switch directory structure, basic file and directory utilities, switch access security, SNMP, and web-based management.
- The software directory architecture.
- Image rollback protections.
- Authenticated switch access.
- Managing switch files.
- System configuration.
- Using SNMP.
- Using web management software (WebView)..

---

**Note.** The maximum limit values provided in the Specifications tables included in this chapter are subject to available system resources.

---

For information about how to configure switch management applications, refer to the *OmniSwitch AOS Release 8 Switch Management Guide*.

## In This Chapter

This chapter contains the following switch management Specifications tables:

- [“Getting Started Specifications” on page 1-3.](#)
- [“Login Specifications” on page 1-3.](#)
- [“File Management Specifications” on page 1-4.](#)
- [“CMM Specifications” on page 1-4.](#)
- [“USB Flash Drive Specifications” on page 1-5.](#)
- [“CLI Specifications” on page 1-5.](#)
- [“Configuration File Specifications” on page 1-6.](#)
- [“User Database Specifications” on page 1-6.](#)
- [“WebView Specifications” on page 1-6.](#)
- [“WebView Specifications” on page 1-6.](#)
- [“SNMP Specifications” on page 1-7.](#)
- [“Web Services Specifications” on page 1-8.](#)
- [“Virtual Chassis Specifications” on page 1-10.](#)
- [“Automatic Remote Configuration Specifications” on page 1-11.](#)
- [“Automatic Fabric Specifications” on page 1-11.](#)
- [“NTP Specifications” on page 1-11.](#)

## Getting Started Specifications

	OS9900	OS6900	OS6860	OS6865	
Standalone Configuration Files	N/S	boot.cfg	N/S	N/S	
Virtual Chassis Configuration Files	vcboot.cfg vcsetup.cfg	vcboot.cfg vcsetup.cfg	vcboot.cfg vcsetup.cfg	vcboot.cfg vcsetup.cfg	
Image Files	Mhost.img Mos.img Meni.img	Tos.img	Uos.img	Uos.img	
<b>Notes:</b>					
N/A.					

## Login Specifications

	OS9900	OS6900	OS6860	OS6865	
Login Methods	Telnet, SSH, HTTP, SNMP				
Number of concurrent Telnet sessions	6				
Number of concurrent SSH sessions	8				
Number of concurrent HTTP (WebView) sessions	4				
Secure Shell public key authentication	Password DSA/RSA Public Key				
RFCs Supported for SSHv2	RFC 4253 - SSH Transport Layer Protocol RFC 4418 - UMAC: Message Authentication Code using Universal Hashing				
<b>Notes:</b>					
N/A					

## File Management Specifications

	OS9900	OS6900	OS6860	OS6865	
File Transfer Methods	FTP (v4/v6), SFTP (v4/v6), SCP (v4/v6), TFTP				
Client/Server Support	FTP—Client (IPv4 Only) or Server SFTP—Client or Server SCP—Client or Server TFTP—Client				
Number of concurrent FTP/SFTP sessions	4				
Configuration Recovery	The <b>flash/certified</b> directory holds configurations that are certified as the default start-up files for the switch. They will be used in the event of a non-specified reload.				
Default Switch Directory - / <b>flash</b>	Contains the <b>certified, working, switch, network</b> , and user-defined directories.				
File/Directory Name Metrics	255 character maximum. File and directory names are case sensitive.				
File/Directory Name Characters	Any valid ASCII character except '/'.				
Sub-Directories	Additional user-defined directories created in the <b>/flash</b> directory.				
Text Editing	Standard Vi editor				
System Clock	Set local date, time and time zone, Universal Time Coordinate (UTC), Daylight Savings (DST or summertime).				
<b>Notes:</b>					
N/A					

## CMM Specifications

	OS9900	OS6900	OS6860	OS6865	
Compact Flash Memory	2 GB	2 GB X72 - 4GB	2 GB	2 GB	
RAM Memory	16 GB	4 GB (X/T) 8 GB (Q32) 8 GB (X72)	2 GB	2 GB	
Maximum Length of File Names (in Characters)	255				
Maximum Length of Directory Names (in Characters)	255				
Maximum Length of System Name (in Characters)	32				
Default Boot Directory	Certified				
<b>Notes:</b>					



N/A

## USB Flash Drive Specifications

	OS9900	OS6900	OS6860	OS6865	
USB Flash Drive Support	Alcatel-Lucent Certified USB Flash Drive				
Automatic Software Upgrade	Supported				
Disaster Recovery	<b>Mrescue.img</b> file required	<b>Trescue.img</b> file required	<b>Urescue.img</b> file required	<b>Urescue.img</b> file required	
<b>Notes:</b>					
The format of the Alcatel-Lucent certified USB Flash Drive must be FAT32. To avoid file corruption issues, the USB Drive should be stopped before removing from a PC. Directory names are case sensitive and must be lower case.					

## CLI Specifications

	OS9900	OS6900	OS6860	OS6865	
Configuration Methods	<ul style="list-style-type: none"> <li>• Online configuration via real-time sessions using CLI commands.</li> <li>• Offline configuration using text file containing CLI commands.</li> </ul>				
Command Capture Feature	Snapshot feature captures switch configurations in a text file.				
User Service Features	<ul style="list-style-type: none"> <li>• Command Line Editing</li> <li>• Command Prefix Recognition</li> <li>• CLI Prompt Option</li> <li>• Command Help</li> <li>• Keyword Completion</li> <li>• Command Abbreviation</li> <li>• Command History</li> <li>• Command Logging</li> <li>• Syntax Error Display</li> <li>• More Command</li> </ul>				
<b>Notes:</b>					
N/A					

## Configuration File Specifications

	OS9900	OS6900	OS6860	OS6865	
Methods for Creating Configuration Files	<ul style="list-style-type: none"> <li>• Create a text file on a word processor and upload it to the switch.</li> <li>• Invoke the switch's snapshot feature to create a text file.</li> <li>• Create a text file using the switch's text editor.</li> </ul>				
Timer Functions	Files can be applied immediately or by setting a timer on the switch.				
Command Capture Feature	Snapshot feature captures switch configurations in a text file.				
Error Reporting	Snapshot feature includes error reporting in the text file.				
Text Editing on the Switch	Vi standard editor.				
Default Error File Limit	1				
<b>Notes:</b>					
N/A					

## User Database Specifications

	OS9900	OS6900	OS6860	OS6865	
Maximum number of alphanumeric characters in a username	63				
Maximum number of alphanumeric characters in a user password	30				
Maximum number of local user accounts	50	50	50	50	
<b>Notes:</b>					
N/A					

## WebView Specifications

	OS9900	OS6900	OS6860	OS6865	
Supported Browsers	Internet Explorer for Windows Firefox for Windows, Linux, and Solaris SunOS				
<b>Notes:</b>					
N/A					

# SNMP Specifications

	OS9900	OS6900	OS6860	OS6865	
RFCs Supported for SNMPv2	1902 through 1907 - SNMPv2c Management Framework 1908 - Coexistence and transitions relating to SNMPv1 and SNMPv2c				
RFCs Supported for SNMPv3	2570—Version 3 of the Internet Standard Network Management Framework 2571—Architecture for Describing SNMP Management Frameworks 2572—Message Processing and Dispatching for SNMP 2573—SNMPv3 Applications 2574/3414—User-based Security Model (USM) for version 3 SNMP 2575—View-based Access Control Model (VACM) for SNMP 2576—Coexistence between SNMP versions 3586—The Advanced Encryption Standard (AES) Cipher Algorithm in the SNMP User-based Security Model				
SNMPv1, SNMPv2, SNMPv3	The SNMPv3 protocol is ascending compatible with SNMPv1 and v2 and supports all the SNMPv1 and SNMPv2 PDUs				
SNMPv1 and SNMPv2 Authentication	Community Strings				
SNMPv1, SNMPv2 Encryption	None				
SNMPv1 and SNMPv2 Security requests accepted by the switch	Sets and Gets				
SNMPv3 Authentication	SHA, MD5				
SNMPv3 Encryption	DES	DES	DES, AES	DES, AES	
SNMPv3 Security requests accepted by the switch	Non-authenticated Sets, Non-authenticated Gets and Get-Nexts, Authenticated Sets, Authenticated Gets and Get-Nexts, Encrypted Sets, Encrypted Gets and Get-Nexts				
SNMP traps	For a list and description of system MIBs and Traps refer to Appendix B, “SNMP Trap Information,” in the <i>OmniSwitch AOS Release 8 Switch Management Guide</i> .				
<b>Notes:</b>					

# Web Services Specifications

	OS9900	OS6900	OS6860	OS6865	
Configuration Methods	<ul style="list-style-type: none"> <li>• HTTP/HTTPS</li> <li>• Python API</li> </ul>				
Response Formats	<ul style="list-style-type: none"> <li>• Extensible Markup language (XML)</li> <li>• JavaScript Object Notation (JSON)</li> </ul>				
Maximum Web Services Sessions	4				
Alcatel-Lucent Example Python Library	<p>consumer.py (Python version 2.X/3.X compatible)</p> <p>This file is available on the Service &amp; Support Website. It is being provided as an example application to help with Web Services familiarization but is not an officially supported part of the Web Services solution.</p>				
Embedded Python /Event based CLI Scripting	Python 3				
<b>Notes:</b>					

# OpenFlow Specifications

	OS9900	OS6900	OS6860	OS6865	
Modes Supported	N/S	Normal Hybrid (API)	Normal Hybrid (API)	N/S	
Versions Supported	N/S	1.0/ 1.3.1	1.0/ 1.3.1	N/S	
Maximum number of logical switches	N/S	3	3	N/S	
Maximum number of controllers per logical switch	N/S	3	3	N/S	
Maximum number of logical switches in Hybrid mode	N/S	1	1	N/S	
Support for Virtual Chassis	N/S	Supported	Supported	N/S	
OpenFlow 1.0/1.3.1 TCP port.	N/S	6633	6633	N/S	
Flow Matching Table	N/S	Q32 - 1279 X72 - 1279 other - 511	1535	N/S	
MAC Table	N/S	Q32 - 224K X72 - 224K other - 128K	48K	N/S	
<b>Notes:</b>					

# Virtual Chassis Specifications

	OS9900	OS6900	OS6860	OS6865	
Maximum number of physical switches in a Virtual Chassis	N/S	6	8	2	
Valid chassis identifier	N/S	1–6	1–8	1 or 2	
Valid chassis group identifier	N/S	0–255	0–255	0–255	
Valid chassis priority	N/S	0–255	0–255	0–255	
Maximum number of Virtual Fabric Link peers per chassis	N/S	5	2	1	
Maximum number of member ports per Virtual Fabric Link	N/S	16	8	2	
Valid Virtual Fabric Link identifier	N/S	0–4	0 or 1	0	
VFL Supported Port Types	N/S	10G SFP+ or 40G QSFP	Dedicated 20G VFL ports or 10G SFP+ ports	10G SFP+ ports	
Valid control VLAN	N/S	2–4094			
Valid Virtual Chassis protocol hello interval	N/S	1–65535			
EMP Address functionality	N/S	N/A	OS6860E only	N/S	
OK LED	Blinking Green = Master Solid Green = Slave				
Remote Chassis Detection (RCD)	N/S	N/S	N/S	N/S	
<b>Notes:</b>					
<ul style="list-style-type: none"> <li>• Different OS6900 models can be mixed in a Virtual Chassis.</li> <li>• MAC Learning Mode is not supported on OS6900 Virtual Chassis</li> <li>• OS9900 does not support a Virtual Chassis configuration.</li> </ul>					

## Automatic Remote Configuration Specifications

	OS9900	OS6900	OS6860	OS6865	
DHCP Specifications	DHCP Server required DHCP Client on: - VLAN 1 - Tagged VLAN 127 - LLDP Management VLAN - Automatic LACP (tagged VLAN 127, untagged VLAN 1)				
File Servers	TFTP FTP/SFTP				
Clients supported	TFTP FTP/SFTP				
Instruction file	Maximum length of: <ul style="list-style-type: none"> <li>• Pathname: 255 characters</li> <li>• Filename: 63 characters</li> </ul>				
Maximum length of username for FTP/SFTP file server.	15 characters				
Maximum DHCP lease tries	6				
Unsupported Features	<ul style="list-style-type: none"> <li>• ISSU and IPv6 are not supported.</li> <li>• Upgrade of uboot, miniboot, or FPGA files is not supported.</li> </ul>				
OK LED	Flashing amber during Automatic Remote Configuration process				
<b>Notes:</b>					
N/A					

## Automatic Fabric Specifications

	OS9900	OS6900	OS6860	OS6865	
Ports Supported	Any switch port that is not already configured in such a way as to prevent the port from participating in the Automatic Fabric discovery and configuration process.				
IP Protocols Supported for Automatic IP Configuration	OSPFv2, OSPFv3, IS-IS IPv4, IS-IS IPv6				
<b>Notes:</b>					
Automatic fabric is not supported on the OS9900.					

## NTP Specifications

	OS9900	OS6900	OS6860	OS6865	
RFCs supported	1305–Network Time Protocol				

---

NTP Key File Location	<b>/flash/network</b>
Maximum number of NTP servers per client	12
<b>Notes:</b>	
N/A	



# 2 Network Configuration Specifications

This chapter provides Specifications tables for the following OmniSwitch network configuration applications and procedures that are used for readying a switch for integration into a live network environment:

- Layer 2 features (Ethernet, source learning, and VLAN configuration).
- Layer 3 features (routing protocols, such as IP and RIP)
- Security options (MAC and 802.1x authentication)
- Quality of Service (QoS)
- Link aggregation
- Server load balancing.

---

**Note.** The maximum limit values provided in the Specifications tables included in this chapter are subject to available system resources.

---

For information about how to implement the fundamental software features and protocols for network configuration, refer to the *OmniSwitch AOS Release 8 Network Configuration Guide*.

## In This Chapter

This chapter contains the following network configuration Specifications tables:

- 
- “Ethernet Specifications” on page 2-3
  - “UDLD Specifications” on page 2-3
  - “Source Learning Specifications” on page 2-4
  - “VLAN Specifications” on page 2-4
  - “High Availability VLANs Specifications” on page 2-5
  - “Spanning Tree Specifications” on page 2-5
  - “Loopback Detection Specifications” on page 2-6
  - “Static Link Aggregation Specifications” on page 2-6
  - “Dynamic Link Aggregation Specifications” on page 2-6
  - “Dual-Home Link Specifications” on page 2-6
  - “ERP Specifications” on page 2-8.
  - “MVRP Specifications” on page 2-8.
  - “802.1AB Specifications” on page 2-8.
  - “SIP Snooping Specifications” on page 2-9.
  - “IP Specifications” on page 2-10.
  - “VRF Specifications” on page 2-11.
  - “IPv6 Specifications” on page 2-12.
  - “IPsec Specifications” on page 2-14.
  - “RIP Specifications” on page 2-15.
  - “BFD Specifications” on page 2-15.
  - “DHCP Relay Specifications” on page 2-16.
  - “DHCP Server Specifications” on page 2-17.
  - “VRRP Specifications” on page 2-18.
  - “Server Load Balancing Specifications” on page 2-18.
  - “IPMS Specifications” on page 2-19.
  - “IPMSv6 Specifications” on page 2-20.
  - “QoS Specifications” on page 2-21.
  - “LDAP Policy Server Specifications” on page 2-22.
  - “Authentication Server Specifications” on page 2-22.
  - “UNP Specifications” on page 2-23.
  - “Access Guardian Specifications” on page 2-24.
  - “AppMon Specifications” on page 2-25.
  - “Application Fingerprinting Specifications” on page 2-25.
  - “Port Mapping Specifications” on page 2-25.
  - “Learned Port Security Specifications” on page 2-25.
  - “Port Mirroring Specifications” on page 2-27.
  - “Port Monitoring Specifications” on page 2-27.
  - “sFlow Specifications” on page 2-28.
  - “RMON Specifications” on page 2-29.
  - “Switch Health Specifications” on page 2-30.
  - “VLAN Stacking Specifications” on page 2-31.
  - “Switch Logging Specifications” on page 2-32.
  - “Ethernet OAM Specifications” on page 2-33.
  - “SAA Specifications” on page 2-33.
-

## Ethernet Specifications

	OS9900	OS6900	OS6860	OS6865	
IEEE Standards Supported	802.3 Carrier Sense Multiple Access with Collision Detection (CSMA/CD) 802.3u (100BaseTX) 802.3ab (1000BaseT) 802.3z (1000Base-X) 802.3ae (10GBase-X) 802.3ba (40GBase-X) 802.3az (Energy Efficient Ethernet)				
Ports Supported	Ethernet (10 Mbps) Fast Ethernet (100 Mbps) Gigabit Ethernet (1 Gbps) 10 Gigabit Ethernet (10 Gbps) 40 Gigabit Ethernet (40 Gbps)				
802.1Q Hardware Tagging	Supported				
Jumbo Frame Configuration	1/10/40 Gigabit Ethernet ports				
Maximum Frame Size	1553 bytes (10/100 Mbps) 9216 bytes (1/10/40 Gbps)				
<b>Notes:</b>					
<ul style="list-style-type: none"> <li>Supported port types are chassis and module dependent.</li> <li>OS6860/6865 does not support 10/100 half-duplex (CSMA/CD)</li> </ul>					

## UDLD Specifications

	OS9900	OS6900	OS6860	OS6865	
Maximum number of UDLD ports per system	Up to maximum physical ports per system.				
<b>Notes:</b>					
UDLD is not supported on the OS9900.					

## Source Learning Specifications

	OS9900	OS6900	OS6860	OS6865	
RFCs Supported	2674—Definitions of Managed Objects for Bridges with Traffic Classes, Multicast Filtering and Virtual LAN Extensions				
Maximum number of learned MAC addresses when centralized MAC source learning mode is enabled	100K	X20 - 128K X40 - 128K T20 - 128K T40 - 128K Q32 - 228K X72 - 228K	48K	48K	
<b>Notes:</b>					
N/A					

## VLAN Specifications

	OS9900	OS6900	OS6860	OS6865	
RFCs Supported	2674 - Definitions of Managed Objects for Bridges with Traffic Classes, Multicast Filtering and Virtual LAN Extensions				
IEEE Standards Supported	802.1Q - Virtual Bridged Local Area Networks 802.1D - Media Access Control Bridges				
Maximum VLANs per switch	4092	4094	4094	4094	
Maximum Tagged VLANs per Port	4091	4093	4093	4093	
Maximum Untagged VLANs per Port	One untagged VLAN (default VLAN) per port.				
Maximum number of ports or link aggregates per PVLAN supported	1				
Maximum Number of Secondary VLANs paired with a Primary VLAN that can co-exist on a port	> 1	1	1	1	
Maximum number of IPCL and EPCL rules per VLAN	256				
Maximum number of PVLAN per promiscuous port	1				
<b>Notes:</b>					
PVLAN is not supported on the OS9900.					

## High Availability VLANs Specifications

	OS9900	OS6900	OS6860	OS6865	
Maximum high availability VLANs per switch	N/S	N/S	16	32	32
<b>Notes:</b>					
N/A					

## Spanning Tree Specifications

	OS9900	OS6900	OS6860	OS6865	
IEEE Standards supported	802.1d—Media Access Control (MAC) Bridges 802.1s—Multiple Spanning Trees 802.1w—Rapid Spanning Tree Protocol				
Spanning Tree operating modes supported	Flat mode—one spanning tree instance per switch Per-VLAN mode—one spanning tree instance per VLAN				
Spanning Tree port eligibility	Fixed ports 802.1Q tagged ports Link aggregate of ports				
Maximum VLAN Spanning Tree instances per switch.	100	128	100	100	
Maximum flat mode Multiple Spanning Tree Instances (MSTI) per switch	16 MSTI, in addition to the Common and Internal Spanning Tree instance (also referred to as MSTI 0).				
<b>Notes:</b>					
Maximum VLAN Spanning Tree instances per switch—values based on per-VLAN mode.					

## Loopback Detection Specifications

	OS9900	OS6900	OS6860	OS6865	
Edge (Bridge)	N/S	N/S	Supported	Supported	
SAP (Access)	N/S	Supported	Supported	Supported	
Transmission Timer	5–600 seconds				
Auto-recovery Timer	30–86400 seconds				
<b>Notes:</b>					
N/A					

## Static Link Aggregation Specifications

	OS9900	OS6900	OS6860	OS6865	
Maximum number of link aggregation groups	2	256	128	128	
Maximum number of ports per link aggregate group	8	16	16	16	
<b>Notes:</b>					
On an OS9900 linkagg IDs 0, 126, and 127 are reserved					

## Dynamic Link Aggregation Specifications

	OS9900	OS6900	OS6860	OS6865	
IEEE Specifications Supported	802.1ax/802.3ad—Aggregation of Multiple Link Segments				
Maximum number of link aggregation groups	42	256	128	128	
Maximum number of ports per link aggregate group	8	16	16	16	
<b>Notes:</b>					
On an OS9900 linkagg IDs 0, 126, and 127 are reserved.					

## Dual-Home Link Specifications

	OS9900	OS6900	OS6860	OS6865	
DHL sessions supported	N/S	N/S	1	1	
<b>Notes:</b>					

N/A
-----

## ERP Specifications

	OS9900	OS6900	OS6860	OS6865	
ITU-T G.8032 03/2010	Ethernet Ring Protection version 2 (Multi Rings and Ladder networks supported) (Hold off timer, Lockout, Signal degrade SD, RPL Replacement, Forced Switch, Manual Switch, Clear for Manual/Forced Switch, Dual end blocking not supported)				
ITU-T Y.1731/IEEE 802.1ag	ERP packet compliant with OAM PDU format for CCM				
Maximum number of rings per node	64				
Maximum number of nodes per ring	16 (recommended)				
Maximum number of VLANs per port	4094				
Range for ring ID	1–2147483647				
Range for remote MEPID	1–8191				
Range for wait-to-restore timer	1–12 minutes				
Range for guard timer	1–200 centi-seconds				
<b>Notes:</b>					
ERP is not supported on the OS9900.					

## MVRP Specifications

	OS9900	OS6900	OS6860	OS6865	
IEEE Standards Supported	IEEE 802.1ak-2007 Amendment 7: Multiple Registration Protocol IEEE 802.1Q-2005 Corrigendum 2008				
Maximum MVRP VLANs	512	512	512	512	
<b>Notes:</b>					

## 802.1AB Specifications

	OS9900	OS6900	OS6860	OS6865	
IEEE Specification	IEEE 802.1AB-2005 Station and Media Access Control Connectivity Discovery				
Maximum number of network policies that can be associated with a port	8	8	8	8	



Maximum number of network policies that can be configured on the switch	32	32	32	32	
Nearest Edge MAC Address	01:20:da:02:01:73				
Nearest Bridge MAC Address	01:80:c2:00:00:0e				
Nearest Customer MAC Address	01:80:C2:00:00:00				
Non-TPMR Address	01:80:C2:00:00:03				
<b>Notes:</b>					
N/A					

## SIP Snooping Specifications

	OS9900	OS6900	OS6860	OS6865	
RFCs Supported	N/S	N/S	3261–SIP session initiation protocol 6337–SIP USAGE of offer/answer model 4566–SDP session description Protocol 3551–RTP profile for audio and video conferences with minimal control 3311–The Session Initiation Protocol (SIP) UPDATE Method 3262–Reliability of Provisional Responses in SIP	N/S	
<b>Notes:</b>					
N/A					

# IP Specifications

	OS9900	OS6900	OS6860	OS6865	
RFCs Supported	791–Internet Protocol 792–Internet Control Message Protocol 826–An Ethernet Address Resolution Protocol 2784–Generic Routing Encapsulation (GRE) 2890–Key and Sequence Number Extensions to GRE (extensions defined are not supported) 1701–Generic Routing Encapsulation (GRE) 1702–Generic Routing Encapsulation over IPV4 Networks 2003-IP Encapsulation within IP				
Maximum router interfaces per system	300	4K IP	4K IP	4K	
Maximum router interfaces per VLAN	16				
Maximum HW routes	128K	X20 - 16K X40 - 16K T20 - 16K T40 - 16K Q32 - 12K X72 - 12K	12K	12K	
Maximum HW ARP entries per module	8K	X20 - 8K X40 - 8K T20 - 16K T40 - 16K Q32 - 48K X72 - 48K	16K	16K	
Maximum HW ARP entries in VC of OS6900s (Distributed ARP not enabled)	N/A	Equal to capacity of module with lowest number of supported ARPs.	N/A	N/A	
Maximum HW ARP entries in VC of OS6900s (Distributed ARP enabled)	N/A	VC of 4 or more (Q32 or X72) - 192K.	N/A	N/A	
Maximum number of GRE tunnel interfaces per switch	N/S	127	127	127	
Maximum number of IPIP tunnel interfaces per switch	N/S	127	127	127	
Maximum next hops per ECMP entry (static or RIP routes)	16	16	16	16	
<b>Notes:</b>					

- The OmniSwitch can support a higher number of routes than what is documented in the hardware routing limits. This is done by moving older unused routes into software and more recent active routes into hardware. The total number of routes supported is dependent upon the switch configuration and the total amount of memory available. Exceeding the maximum hardware routes will result in some traffic being routed in software.

## VRF Specifications

	OS9900	OS6900	OS6860	OS6865	
Routing Protocols Supported	Static, IPv4, RIPv2, OSPFv2, BGP4, IS-IS			Static, IPv4, RIPv2, OSPFv2, BGP4	
Maximum number of MAX profile VRF instances per switch (no LOW profiles)	64	64	64	64	
Maximum number of LOW profile VRF instances per switch (no MAX profiles)	300	128	128	128	
Maximum VRF instances per VLAN	1				
Maximum OSPFv2 VRF routing instances per switch	16				
Maximum RIPv2 VRF routing instances per switch	16				
Maximum BGP VRF routing instances per switch	32				
<b>Notes:</b>					

# IPv6 Specifications

	OS9900	OS6900	OS6860	OS6865	
RFCs Supported	1981—Path MTU Discovery for IP version 6 2375—IPv6 Multicast Address Assignments 2460—Internet Protocol, Version 6 (IPv6) Specification 2464—Transmission of IPv6 Packets over Ethernet Networks 2465—Management Information Base for IP Version 6: Textual Conventions and General Group 2466—Management Information Base for IP Version 6: ICMPv6 Group 2711—IPv6 Router Alert Option 3056—Connection of IPv6 Domains via IPv4 Clouds 3484—Default Address Selection for Internet Protocol version 6 (IPv6) 3493—Basic Socket Interface Extensions for IPv6 3542—Advanced Sockets Application Program Interface (API) for IPv6 3587—IPv6 Global Unicast Address Format 3595—Textual Conventions for IPv6 Flow Label 3596—DNS Extensions to Support IP Version 6 4007—IPv6 Scoped Address Architecture 4022—Management Information Base for the Transmission Control Protocol (TCP) 4113—Management Information Base for the User Datagram Protocol (UDP) 4193—Unique Local IPv6 Unicast Addresses 4213—Basic Transition Mechanisms for IPv6 Hosts and Routers 4291—IP Version 6 Addressing Architecture 4294—IPv6 Node Requirements 4443—Internet Control Message Protocol (ICMPv6) for the Internet Protocol Version 6 (IPv6) Specification 4861—Neighbor Discovery for IP version 6 (IPv6) 4862—IPv6 Stateless Address Autoconfiguration 5095—Deprecation of Type 0 Routing Headers in IPv6 5453—Reserved IPv6 Interface Identifiers 5722—Handling of Overlapping IPv6 Fragments 3315—Dynamic Host Configuration Protocol for IPv6 (DHCPv6)				
Maximum IPv6 interfaces	VLANs- 4096 Configured Tunnels - 255 6to4 Tunnels - 1				
Maximum IPv6 global unicast or anycast addresses	N/S	10K	10K	10K	
Maximum IPv6 global unicast addresses per IPv6 interface	N/S	50	50	50	
Maximum IPv6 addresses assigned through VRRP configuration	N/S	1K	1K	1K	

Maximum IPv6 hardware routes when there are no IPv4 routes present (includes dynamic and static routes)	N/S	256 (prefix >= 65) X20/ X40 - 8K (prefix <= 64) T20/ T40 - 8K (prefix <= 64) Q32/ X72 - 6K (prefix <=64)	1K (prefix >= 65) 6K (prefix <= 64)	1K (prefix >= 65) 6K (prefix <= 64)	
Maximum IPv6 static route prefixes per switch	N/S	500	500	500	
Maximum Number of RIPng Peers	N/S	10	10	10	
Maximum Number of RIPng Interfaces	N/S	10	10	10	
Maximum Number of RIPng Routes	N/S	5K	5K	5K	
Maximum next hops per ECMP entry (static or RIPng routes)	N/S	16	16	16	
DHCPv6 Implementation	N/S	N/S	multi-VRF		
DHCPv6 Relay Implementation	N/S	N/S	IPv6 Interface (VLAN, configured tunnel, 6to4 tunnel)		
DHCPv6 Relay Service	N/S	N/S	DHCPv6, UDPv6		
Maximum IPv6 relay destinations supported for each Interface	N/S	N/S	5	5	
Maximum number of Relay Hops for each relay	N/S	N/S	32	32	
<b>Notes:</b>					
<ul style="list-style-type: none"> <li>• RFC 3315 is not supported on the OS6900 switches.</li> <li>• Exceeding the maximum IPv6 hardware routes or having IPv4 routes will result in some traffic being routed in software.</li> </ul>					

# IPsec Specifications

	OS9900	OS6900	OS6860	OS6865	
IP Version Supported	IPv6				
RFCs Supported	4301—Security Architecture for the Internet Protocol 4302—IP Authentication Header (AH) 4303—IP Encapsulating Security Payload (ESP) 4305—Cryptographic Algorithm Implementation Requirements for ESP and AH 4308—Cryptographic Suites for IPsec				
Encryption Algorithms Supported for ESP	NULL, 3DES-CBC, and AES-CBC				
Key lengths supported for Encryption Algorithms	3DES-CBC - 192 bits AES-CBC - 128, 192, or 256 bits				
Authentication Algorithms Supported for AH	HMAC-SHA1-96, HMAC-MD5-96, and AES-XCBC-MAC-96				
Key lengths supported for Authentication Algorithms	HMAC-MD5 - 128 bits HMAC-SHA1 - 160 bits AES-XCBC-MAC - 128 bits				
Master Security Key formats	Hexadecimal (16 bytes) or String (16 characters)				
Priority value range for IPsec Policy	1–1000 (1=highest priority, 1000=lowest priority)				
Index value range for IPsec Policy Rule	1–10				
SPI Range	256–999999999				
Modes Supported	Transport				
<b>Notes:</b>					

## RIP Specifications

	OS9900	OS6900	OS6860	OS6865	
RFCs Supported	RFC 1058–RIP v1 RFC 2453–RIP v2 RFC 1722–RIP v2 Protocol Applicability Statement RFC 1724–RIP v2 MIB Extension				
Maximum Number of Interfaces	16	10	10	10	
Maximum Number of Peers	16	100	100	100	
Maximum Number of Routes	10K	10K	10K	10K	
Maximum number of ECMP next hop entries	512	16	16	16	
<b>Notes:</b>					

## BFD Specifications

	OS9900	OS6900	OS6860	OS6865	
RFCs Supported	5880—Bidirectional Forwarding Detection 5881—Bidirectional Forwarding Detection for IPv4 and IPv6 (Single Hop) 5882—Generic Application of Bidirectional Forwarding Detection				
Maximum Number of BFD Sessions	N/S	Chassis - 32 VC - 100	Chassis - 32 VC - 100	Chassis - 32 VC - 100 -	
Protocols Supported	BGP, OSPF, VRRP Remote Address Tracking only, and Static Routes. IPv6 protocols not supported.				
Modes Supported	Asynchronous Echo (Demand Mode not supported)				
<b>Notes:</b>					
<ul style="list-style-type: none"> <li>• BFD is not supported on the OS9900.</li> </ul>					

## DHCP Relay Specifications

	OS9900	OS6900	OS6860	OS6865	
RFCs Supported	0951–Bootstrap Protocol 1534–Interoperation between DHCP and BOOTP 1541–Dynamic Host Configuration Protocol 1542–Clarifications and Extensions for the Bootstrap Protocol 2132–DHCP Options and BOOTP Vendor Extensions 3046–DHCP Relay Agent Information Option, 2001				
DHCP Relay Implementation	Global DHCP Per-VLAN DHCP				
DHCP Relay Service	BOOTP/DHCP (Bootstrap Protocol/Dynamic Host Configuration Protocol)				
UDP Port Numbers	67 for Request 68 for Response				
IP addresses supported for each Relay Service	Maximum of 256 IP addresses for each Relay Service.				
IP addresses supported for the Per-VLAN service	Maximum of 256 VLAN relay services.				
Maximum number of UDP relay services allowed per switch	10				
Maximum number of VLANs to which forwarded UDP service port traffic is allowed	256				
<b>Notes:</b>					
N/A					



# DHCP Server Specifications

	OS9900	OS6900	OS6860	OS6865	
RFCs Supported	RFC 2131—Dynamic Host Configuration Protocol RFC 3315—Dynamic Host Configuration Protocol for IPv6 RFC 950—Internet Standard Subnetting Procedure RFC 868—Time Protocol RFC 1035—Domain Implementation and Specification RFC 1191—Path MTU Discovery				
DHCP Server Implementation	BOOTP/DHCP				
UDP Port Numbers	67 for Request and Response (IPv4) 547 for Request (IPv6) 546 for Response (IPv6)				
IP address lease allocation mechanisms:					
<b>BootP</b>	<b>Static BootP:</b> IP address is allocated using the BootP configuration when the MAC address of the client is defined.				
<b>DHCP</b>	<b>Static DHCP:</b> The network administrator assigns an IP address to the client. DHCP conveys the address assigned by the DHCP server to the client.  <b>Dynamic DHCP:</b> The DHCP server assigns an IP address to a client for a limited period of time or until the client explicitly releases the address.				
OmniSwitch IPv4 Configuration Files	<b>dhcpd.conf</b> <b>dhcpd.pcy</b> <b>dhcpsrv.db</b>				
OmniSwitch IPv6 Configuration Files	<b>dhcpdv6.conf</b> <b>dhcpdv6.pcy</b> <b>dhcpv6srv.db</b>				
Maximum number of leases	8000				
Maximum lease information file size	375K				
<b>Notes:</b>					
<ul style="list-style-type: none"> <li>DHCP server is not supported on the OS9900.</li> </ul>					

## VRRP Specifications

	OS9900	OS6900	OS6860	OS6865	
RFCs Supported	RFC 3768—Virtual Router Redundancy Protocol RFC 2787—Definitions of Managed Objects for the Virtual Router Redundancy Protocol				
Compatible with HSRP	No				
Maximum number of VRRPv2 and VRRPv3 virtual routers	134	255	255	255	
Maximum number of IP addresses per instance	-	16	16	16	
<b>Notes:</b>					

## Server Load Balancing Specifications

	OS9900	OS6900	OS6860	OS6865	
Maximum number of clusters	32				
Maximum number of physical servers per cluster	32				
Layer-3 classification	Destination IP address QoS policy condition				
Layer-2 classification	QoS policy condition				
Server health checking	Ping, link checks				
High availability support	Hardware-based failover, VRRP, Chassis Management Module (CMM) redundancy				
Networking protocols supported	Virtual IP (VIP) addresses				
<b>Notes:</b>					
<ul style="list-style-type: none"> <li>• SLB is not supported on the OS9900.</li> </ul>					

# IPMS Specifications

	OS9900	OS6900	OS6860	OS6865	
RFCs Supported	RFC 1112—Host Extensions for IP Multicasting RFC 2236—Internet Group Management Protocol, Version 2 RFC 2710—Multicast Listener Discovery (MLD) for IPv6 RFC 2933—Internet Group Management Protocol MIB RFC 3019—IP Version 6 Management Information Base for The Multicast Listener Discovery Protocol RFC 3376—Internet Group Management Protocol, Version 3 RFC 3810—Multicast Listener Discovery Version 2 (MLDv2) for IPv6 RFC 4541—Considerations for Internet Group Management Protocol (IGMP) and Multicast Listener Discovery (MLD) Snooping Switches RFC 4604—Using Internet Group Management Protocol Version 3 (IGMPv3) and Multicast Listener Discovery Protocol Version 2 (MLDv2) for Source-Specific Multicast				
IGMP Versions Supported	IGMPv1, IGMPv2, IGMPv3				
Maximum number of IPv4 multicast flows	2K	X20 - 2K X40 - 2K T20 - 2K T40 - 2K Q32 - 20K X72 - 20K	12K	12K	
Maximum number of IPv4 multicast forwarding entries	3K	40K	8K	8K	
<b>Notes:</b>					
Mixing an XNI-U32S with other modules in the same chassis reduces the maximum number of IPv4 multicast flows to 2K.					

# IPMSv6 Specifications

	OS9900	OS6900	OS6860	OS6865	
RFCs Supported	RFC 2710—Multicast Listener Discovery for IPv6 RFC 3019—IPv6 MIB for Multicast Listener Discovery Protocol RFC 3306—Unicast-Prefix-based IPv6 Multicast Addresses RFC 3810—Multicast Listener Discovery Version 2 for IPv6 RFC 4541—Considerations for Internet Group Management Protocol (IGMP) and Multicast Listener Discovery (MLD) Snooping Switches RFC 4604—Using Internet Group Management Protocol Version 3 (IGMPv3) and Multicast Listener Discovery Protocol Version 2 (MLDv2) for Source-Specific Multicas				
MLD Versions Supported	MLDv1, MLDv2				
MLD Query Interval	1–65535 in seconds				
MLD Router Timeout	1–65535 in seconds				
MLD Source Timeout	1–65535 in seconds				
MLD Query Response Interval	1–65535 in milliseconds				
MLD Last Member Query Interval	1–65535 in milliseconds				
Maximum number of IPv6 multicast flows	N/S	X20 - 2K X40 - 2K T20 - 2K T40 - 2K Q32 - 20K X72 - 20K	12K	12K	
<b>Notes:</b>					
<ul style="list-style-type: none"> <li>• IPMSv6 is not supported on the OS9900.</li> <li>• Mixing an XNI-U32S with other modules in the same chassis reduces the maximum number of IPv4 multicast flows to 2K.</li> </ul>					

# QoS Specifications

	OS9900	OS6900	OS6860	OS6865	
Maximum number of policy rules	512	8192	3072	3072	
Maximum number of policy conditions	512	8192	-	-	
Maximum number of policy actions	512	8192	-	-	
Maximum number of policy rules per slot	512	1024 Q32 - 2560 X72 - 2560	-	-	
Maximum number of bandwidth policy rules	512	512	1536	-	
Maximum number of validity periods	64				
Maximum number of policy services	256				
Maximum number of groups (network, MAC, service, port)	1024	2048	1024	-	
Maximum number of group entries	1024	1024 per group (512 per service group)	1024 per group	-	
Maximum number of Class of Service (CoS) queues per port.	8				
Queue Set Profiles (QSP)	4				
Weighted Random Early Detection profiles (WRED)	-	TCP traffic only Q32- N/S X72 - N/S	N/S	N/S	
Maximum number of QoS policy lists per switch	32 (includes the default list)				
Maximum number of QoS policy lists per Universal Network Profile (UNP)	1				
Port Default Trusted Mode	Untrusted				
<b>Notes:</b>					
N/A					

## LDAP Policy Server Specifications

	OS9900	OS6900	OS6860	OS6865	
RFCs Supported	RFC 2251–Lightweight Directory Access Protocol (v3) RFC 3060–Policy Core Information Model—Version 1 Specification				
Maximum number of policy servers (supported on the switch)	5				
Maximum number of policy servers (supported by PolicyView)	1				
<b>Notes:</b>					
N/A					

## Authentication Server Specifications

	OS9900	OS6900	OS6860	OS6865	
RADIUS RFCs Supported	RFC 2865–Remote Authentication Dial In User Service (RADIUS) RFC 2866–RADIUS Accounting RFC 2867–RADIUS Accounting Modifications for Tunnel Protocol Support RFC 2868–RADIUS Attributes for Tunnel Protocol Support RFC 2809–Implementation of L2TP Compulsory Tunneling through RADIUS RFC 2869–RADIUS Extensions RFC 2548–Microsoft Vendor-specific RADIUS Attributes RFC 2882–Network Access Servers Requirements: Extended RADIUS Practices				
TACACS+ RFCs Supported	RFC 1492–An Access Control Protocol				
LDAP RFCs Supported	RFC 1789–Connectionless Lightweight X.5000 Directory Access Protocol RFC 2247–Using Domains in LDAP/X.500 Distinguished Names RFC 2251–Lightweight Directory Access Protocol (v3) RFC 2252–Lightweight Directory Access Protocol (v3): Attribute Syntax Definitions RFC 2253–Lightweight Directory Access Protocol (v3): UTF-8 String Representation of Distinguished Names RFC 2254–The String Representation of LDAP Search Filters RFC 2256–A Summary of the X.500(96) User Schema for Use with LDAPv3				
Other RFCs	RFC 2574–User-based Security Model (USM) for version 3 of the Simple Network Management Protocol (SNMPv3) RFC 2924–Accounting Attributes and Record Formats RFC 2975–Introduction to Accounting Management RFC 2989–Criteria for Evaluating AAA Protocols for Network Access				

Maximum number of authentication servers in single authority mode	8
Maximum number of authentication servers in multiple authority mode	8
Maximum number of servers per Authenticated Switch Access type	8
<b>Notes:</b>	
N/A	

## UNP Specifications

	OS9900	OS6900	OS6860	OS6865
Number of UNPs per switch	1K	4K	1K	1K
Number of UNP users per switch	1K	2K	256	256
Authentication type	MAC and 802.1x authentication			
Profile type	VLAN, SPB service, and VXLAN service		Edge, VLAN, and SPB service	
UNP port type	Bridge (VLAN-based classification) or access (service-based classification)		Edge, bridge, and SPB access	
UNP classification rules	MAC address, MAC address range, IP address, and VLAN tag		MAC address, MAC OUI, MAC address range, IP address, VLAN tag, Port, Group ID, authentication type, and LLDP (IP Phones TLV)	
Number of QoS policy lists per switch	32 (includes the default list)			
Number of QoS policy lists per UNP	1			
<b>Notes:</b>				
Number of UNPs per switch includes static and dynamic profiles.				

# Access Guardian Specifications

	OS9900	OS6900	OS6860	OS6865	
RFCs Supported	RFC 2284–PPP Extensible Authentication Protocol (EAP) RFC 2865–Remote Authentication Dial In User Service (RADIUS) RFC 2866–RADIUS Accounting RFC 2867–RADIUS Accounting Modifications for Tunnel Protocol Support RFC 2868–RADIUS Attributes for Tunnel Protocol Support RFC 2869–RADIUS Extensions RFC 3576--Change of Authorization-Request (COA) and Disconnect request (DM) for BYOD. RFC support is limited to ClearPass solution. RFC 3579–RADIUS Support for EAP				
IEEE Standards Supported	IEEE 802.1X-2001–Standard for Port-based Network Access Control 802.1X RADIUS Usage Guidelines				
Authentication methods supported	N/S	N/S	802.1X, MAC address, Captive Portal		
Maximum number of Access Guardian users	N/S	N/S	1K (includes quarantined and Captive Portal users)		
Maximum number of users quarantined by QMR	N/S	N/S	1K	1K	
Average number of users allowed to login to Captive portal Web pages at any given time	N/S	N/S	40	40	
Maximum number of Captive Portal profiles	N/S	N/S	8	8	
Maximum number of AAA profiles	N/S	N/S	8	8	
Maximum number of authentication servers	N/S	N/S	4 per authentication type (MAC, 802.1X, Captive Portal)		
Maximum number of accounting servers	N/S	N/S	4 per authentication type (MAC, 802.1X, Captive Portal)		
BYOD Solution Server	N/S	N/S	ClearPass Policy Manager (CPPM)		
mDNS GRE Tunnel Supported Protocol	N/S	N/S	IPv4	IPv4	
SSDP GRE Tunnel Supported Protocol	N/S	N/S	IPv4	IPv4	
<b>Notes:</b>					
<ul style="list-style-type: none"> <li>Access Guardian BYOD related features are only supported on the OS6860/6865.</li> </ul>					



## AppMon Specifications

	OS9900	OS6900	OS6860	OS6865	
Packet types sampled	N/S	N/S	TCP and UDP		
<b>Notes:</b>					
<ul style="list-style-type: none"> <li>AppMon is supported in a virtual chassis of OmniSwitch 6860 and OmniSwitch 6860E platforms where at least one OmniSwitch 6860E is mandatory for the feature to work.</li> </ul>					

## Application Fingerprinting Specifications

	OS9900	OS6900	OS6860	OS6865
Packet sampling rate	50K packets-per-second on each module.		N/S	
Packet types sampled	IPv4 and IPv6 (no fragmented, encrypted, control, or protocol packets. For example, ICMP, LLDP, BPDU packets not scanned).		N/S.	
<b>Notes:</b>				
<ul style="list-style-type: none"> <li>AFP is supported on the OS6900 only.</li> </ul>				

## Port Mapping Specifications

	OS9900	OS6900	OS6860	OS6865	
Port Mapping Sessions	8				
<b>Notes:</b>					
Port mapping is not supported on the OS9900.					

## Learned Port Security Specifications

	OS9900	OS6900	OS6860	OS6865	
Ports eligible for Learned Port Security	Fixed and 802.1Q tagged				
Ports not eligible for Learned Port Security	Link aggregate ports. 802.1Q (trunked) link aggregate ports.				
Minimum number of learned MAC addresses allowed per LPS port	1				

Maximum number of learned MAC addresses allowed per LPS port	1000
Maximum number of filtered MAC addresses allowed per LPS port	100
Maximum number of configurable MAC address ranges per LPS port	1
<b>Notes:</b>	

## Port Mirroring Specifications

	OS9900	OS6900	OS6860	OS6865
Mirroring Sessions Supported	2	2	2	2
Combined Mirroring/ Monitoring Sessions per Chassis	3	2	2	3
N-to-1 Mirroring Supported	128 to 1	128 to 1	128 to 1	128 to 1
Number of RPMIR VLANs per session	N/S	1	1	1
<b>Notes:</b>				
N/A				

## Port Monitoring Specifications

	OS9900	OS6900	OS6860	OS6865	
Monitoring Sessions Supported	1	1	1	1	
Combined Mirroring/ Monitoring Sessions per Chassis	3	2	2	2	
File Type Supported	ENC file format (Network General Sniffer Network Analyzer Format)				
<b>Notes:</b>					
N/A					

# sFlow Specifications

	OS9900	OS6900	OS6860	OS6865	
RFCs Supported	3176—sFlow Management Information Base				
Receiver/Sampler/Polling Instances	2				
Sampling	length of packet type of frame source and destination MACs source and destination VLANs source and destination priorities source and destination IP addresses source and destination ports tcp flags and tos				
Polling	In octets Out octets Number of Rx Unicast packets Number of Tx Unicast packets Number of Rx Multicast packets Number of Tx Multicast packets Number of Rx Broadcast packets Number of Tx Broadcast packets In Errors Out Errors				
<b>Notes:</b>					
- Sflow not supported on OS9900.					

# RMON Specifications

	OS9900	OS6900	OS6860	OS6865	
RFCs Supported	2819 - Remote Network Monitoring Management Information Base				
RMON Functionality Supported	Basic RMON 4 group implementation –Ethernet Statistics group –History (Control and Statistics) group –Alarms group –Events group				
RMON Functionality Not Supported	RMON 10 group* RMON2* –Host group –HostTopN group –Matrix group –Filter group –Packet Capture group (*An external RMON probe that includes RMON 10 group and RMON2 be used where full RMON probe functionality is required.)				
Flavor (Probe Type)	Ethernet/History/Alarm				
Status	Active/Creating/Inactive				
History Control Interval (seconds)	1–3600				
History Sample Index Range	1–65535				
Alarm Interval (seconds)	1–2147483647				
Alarm Startup Alarm	Rising Alarm/Falling Alarm/ RisingOrFalling Alarm				
Alarm Sample Type	Delta Value/Absolute				
RMON Traps Supported	RisingAlarm/FallingAlarm These traps are generated whenever an Alarm entry crosses either its Rising Threshold or its Falling Threshold and generates an event configured for sending SNMP traps.				
<b>Notes:</b>					
N/A					

## Switch Health Specifications

	OS9900	OS6900	OS6860	OS6865	
Health Functionality Supported	<ul style="list-style-type: none"> <li>–Switch level CPU Utilization Statistics (percentage);</li> <li>–Switch/module/port level Input Utilization Statistics (percentage);</li> <li>–Switch/module/port level Input/Output Utilization Statistics (percentage);</li> <li>–Switch level Memory Utilization Statistics (percentage);</li> <li>–Device level (for example, Chassis/CMM) Temperature Statistics (Celsius).</li> </ul>				
Monitored Resource Utilization Levels	<ul style="list-style-type: none"> <li>–Most recent utilization level;</li> <li>–Average utilization level during last minute;</li> <li>–Average utilization level during last hour;</li> <li>–Maximum utilization level during last hour.</li> </ul>				
Resource Utilization Raw Sample Values	Saved for previous 60 seconds.				
Resource Utilization Current Sample Values	Stored.				
Resource Utilization Maximum Utilization Value	Calculated for previous 60 seconds and stored.				
Utilization Value = 0	Indicates that none of the resources were measured for the period.				
Utilization Value = 1	Indicates that a non-zero amount of the resource (less than 2%) was measured for the period.				
Percentage Utilization Values	Calculated based on Resource Measured During Period/Total Capacity.				
Resource Threshold Levels	Apply automatically across all levels of switch (switch/module/port).				
Rising Threshold Crossing	A Resource Threshold was exceeded by its corresponding utilization value in the current cycle.				
Falling Threshold Crossing	A Resource Threshold was exceeded by its corresponding utilization value in the previous cycle, but is not exceeded in the current cycle.				
Threshold Crossing Traps Supported	Device, module, port-level threshold crossings.				
<b>Notes:</b>					
N/A					

## VLAN Stacking Specifications

	OS9900	OS6900	OS6860	OS6865
IEEE Standards supported	IEEE 802.1Q, 2003 Edition, IEEE Standards for Local and Metropolitan Area Networks—Virtual Bridged Local Area Networks P802.1ad/D6.0 (C/LM) Standard for Local and Metropolitan Area Networks—Virtual Bridged Local Area Networks—Amendment 4: Provider Bridges			
Maximum number of services	4			
Maximum number of SVLANs	4K			
Maximum number of SAPs	8K			
Maximum number of SAP profiles	8K (1K if profiles assign priority or bandwidth)		8K	8K
Maximum number of SAP profile VLAN translation or double tagging rules	8K		-	-
Maximum number of customer VLANs (CVLANs) associated with a SAP	4K			
Maximum number of service-to-SAP associations	-	-	-	1K
<b>Notes:</b>				
VLAN Stacking is not supported on the OS9900.				

## Switch Logging Specifications

	OS9900	OS6900	OS6860	OS6865	
RFCs Supported	RFC-5424 Syslog Protocol				
Functionality Supported	High-level event logging mechanism that forwards requests from applications to enabled logging devices.				
Number of Syslog Servers Supported	12				
Logging Devices	Flash Memory/Console/IP Address				
Severity Levels/Types Supported	2 (Alarm - highest severity), 3 (Error), 4 (Alert), 5 (Warning) 6 (Info - default), 7 (Debug 1), 8 (Debug 2), 9 (Debug 3 - lowest severity)				
<b>Notes:</b>					
N/A					



## Ethernet OAM Specifications

	OS9900	OS6900	OS6860	OS6865	
Standards Supported	IEEE 802.1ag Version 8.1– <i>Connectivity Fault Management</i> IEEE 802.1D– <i>Media Access Control (MAC) Bridges</i> IEEE 802.1Q– <i>Virtual Bridged Local Area Networks</i> ITU-T Y.1731– <i>OAM Functions and Mechanisms for Ethernet-Based Networks</i>				
Maximum Maintenance Domains (MD) per Bridge	8				
Maximum Maintenance Associations (MA) per Bridge	128				
Maximum Maintenance End Points (MEP) per Bridge	256				
Maximum MEP CMM Database Size	1K				
Minimum CCM interval	100ms				
<b>Notes:</b>					
Ethernet OAM is not supported on the OS9900.					

## SAA Specifications

	OS9900	OS6900	OS6860	OS6865	
Platforms Supported	N/S	Supported	Supported	Supported	
<b>Notes:</b>					
N/A					

# 3 Advanced Routing Configuration Specifications

This chapter provides Specifications tables for the following OmniSwitch features that are used to set up and monitor advanced routing protocols for operation in a live network environment:

- Routing technologies.
  - Open Shortest Path First (OSPF), version 2 and version 3.
  - Intermediate System-to-Intermediate System (IS-IS).
  - Border Gateway Protocol (BGP).
- Multicast routing protocols.
  - Multicast boundaries that are used to confine scoped multicast addresses to a specific domain.
  - Distance Vector Multicast Routing Protocol (DVMRP)
  - Protocol-Independent Multicast (PIM)
  - Multicast Border Router (MBR) functionality as defined in the PIM-SM specification (RFC 4601)

**Note:** The OmniSwitch can support a higher number of routes than what is documented in the protocol routing tables. The values documented are based on typical scenarios and validated during the AOS test phase. The total number of routes supported is dependent upon the switch configuration and the total amount of memory available.

For information about how to configure advanced routing protocols, refer to the *OmniSwitch AOS Release 8 Advanced Routing Configuration Guide*.

## In This Chapter

This chapter contains the following Advanced Routing Specifications tables:

- [“OSPF Specifications” on page 3-2.](#)
- [“OSPFv3 Specifications” on page 3-3.](#)
- [“IS-IS Specifications” on page 3-4.](#)
- [“BGP Specifications” on page 3-5.](#)
- [“Multicast Boundary Specifications” on page 3-6.](#)
- [“DVMRP Specifications” on page 3-6.](#)
- [“PIM Specifications” on page 3-7.](#)
- [“MBR Specifications” on page 3-8.](#)

# OSPF Specifications

The following Specifications table contains information for the OmniSwitch implementation of Open Shortest Path First (OSPF) routing protocol. Note that any maximum limits provided in the table are subject to available system resources.

	OS9900	OS6900	OS6860	OS6865	
RFCs supported	1370—Applicability Statement for OSPF 4750—OSPF Version 2 Management Information Base 2328—OSPF Version 2 5250—The OSPF Opaque LSA Option 3101—The OSPF Not-So-Stubby Area (NSSA) Option 3623—Graceful OSPF Restart				
Maximum number of areas	10	10	4	4	
Maximum number of interfaces	128	128	128	128	
Maximum number of passive interfaces	200	200	200	200	
Maximum number of Link State Database entries	-	100K	20K	20K	
Maximum number of neighbors per router	254	254	128	128	
Maximum number of routes	14K	32K	32K	32K	
Maximum number of ECMP next hop entries	2	16	16	16	
<b>Notes:</b>					
- The maximum number of routes value may vary depending on the number of interfaces/neighbors.					

## OSPFv3 Specifications

The following Specifications table contains information for the OmniSwitch implementation of Open Shortest Path First version 3 (OSPFv3) routing protocol. Note that any maximum limits provided in the table are subject to available system resources.

	OS9900	OS6900	OS6860	OS6865	
RFCs supported	RFC 1826—IP Authentication Header RFC 1827—IP Encapsulating Security Payload RFC 2553—Basic Socket Interface Extensions for IPv6 RFC 2373—IPv6 Addressing Architecture RFC 2374—An IPv6 Aggregatable Global Unicast Address Format RFC 2460—IPv6 base specification RFC 2740—OSPF for IPv6				
Maximum number of areas	N/S	5	4	4	
Maximum number of interfaces	N/S	20	128	128	
Maximum number of Link State Database entries	N/S	20K	20K	20K	
Maximum number of neighbors	N/S	128	128	128	
Maximum number of routes	N/S	10K	32K	32K	
Maximum number of ECMP next hop entries	N/S	16	16	16	
<b>Notes:</b>					
- The maximum number of routes per router value may vary depending on the number of interfaces/neighbors.					

## IS-IS Specifications

The following Specifications table contains information for the OmniSwitch implementation of the Intermediate System-to-Intermediate System (IS-IS) routing protocol. Note that any maximum limits provided in the table are subject to available system resources.

	OS9900	OS6900	OS6860	OS6865	
RFCs Supported	1142-OSI IS-IS Intra-domain Routing Protocol 1195-OSI IS-IS for Routing in TCP/IP and Dual Environments 3373-Three-Way Handshake for Intermediate System to Intermediate System (IS-IS) Point- to-Point Adjacencies 3567-Intermediate System to Intermediate System (IS-IS) Cryptographic Authentication 2966-Prefix Distribution with two-level IS-IS (Route Leaking) support 2763-Dynamic Host name exchange support 3719-Recommendations for Interoperable Networks using IS-IS 3787-Recommendations for Interoperable IP Networks using IS-IS 5308-IS-IS support for IPv6 (Routing IPv6 with IS-IS)				
IETF Internet-Drafts Supported	draft-ietf-isis-igp-p2p-over-lan-05.txt-Point-to-point operation over LAN in link-state routing protocols				
Maximum number of areas (per router)	N/S	3	3	3	
Maximum number of L1 adjacencies per interface (per router)	N/S	70	70	70	
Maximum number of L2 adjacencies per interface (per router)	N/S	70	70	70	
Maximum number of IS-IS interfaces (per router)	N/S	70	70	70	
Maximum number of Link State Packet entries (per adjacency)	N/S	255	255	255	
Maximum number of IS-IS routes	N/S	24000	24000	24000	
Maximum number of IS-IS L1 routes	N/S	12000	12000	12000	
Maximum number of IS-IS L2 routes	N/S	12000	12000	12000	
<b>Notes:</b>					

# BGP Specifications

The following Specifications table contains information for the OmniSwitch implementation of the Border Gateway Protocol (BGP) routing protocol. Note that any maximum limits provided in the table are subject to available system resources.

	OS9900	OS6900	OS6860	OS6865	
RFCs Supported	1771/4271–A Border Gateway Protocol 4 (BGP-4) 2439–BGP Route Flap Damping 3392/5492–Capabilities Advertisement with BGP-4 2385–Protection of BGP Sessions via the TCP MD5 Signature Option 1997–BGP Communities Attribute 4456–BGP Route Reflection: An Alternative to Full Mesh Internal BGP (IBGP) 3065–Autonomous System Confederations for BGP 4273–Definitions of Managed Objects for BGP-4 4486–Subcodes for BGP Cease Notification 4760–Multiprotocol Extensions for BGP-4 2545–Use of BGP-4 Multiprotocol Extensions for IPv6 Inter-Domain Routing 2918 - Route Refresh Capability for BGP-4 4724 - Graceful Restart Mechanism for BGP 6793 - BGP 4-octet ASN 5668 - 4-Octet AS Specific BGP Extended Community 2042 - Registering New BGP Attribute Types 5396 -Textual Representation of Autonomous System (AS) Numbers				
BGP Attributes Supported	Origin, AS Path, Next Hop (IPv4), MED, Local Preference, Atomic Aggregate, Aggregator (IPv4), Community, Originator ID, Cluster List, Multiprotocol Reachable NLRI (IPv6), Multiprotocol Unreachable NLRI (IPv6), AS4 Path, AS4 Aggregator (IPv4), and AS Specific Extended Community.				
Maximum number of peers per switch (32 peers per VRF)	30	512	512	512	
Maximum number of networks	-	4K	4K	4K	
Maximum number of aggregation addresses	-	2K	2K	2K	
Maximum number of routes	20K	128K	64K	64K	
Maximum number of policies	-	1K	1K	1K	
<b>Notes:</b>					

## Multicast Boundary Specifications

The following Specifications table contains information for the OmniSwitch implementation of multicast address boundary functionality. Note that any maximum limits provided in the table are subject to available system resources.

	OS9900	OS6900	OS6860	OS6865	
RFCs Supported	2365—Administratively Scoped IP Multicast 5132 - IP Multicast MIB				
Valid Scoped Address Range	239.0.0.0 to 239.255.255.255				
Valid extended Multicast route boundary Address Range	224.0.0.0 to 239.255.255.255				
<b>Notes:</b>					
If software routing is used, the number of total flows supported is variable, depending on the number of flows and the number of routes per flow.					

## DVMRP Specifications

The following Specifications table contains information for the OmniSwitch implementation of the Distance Vector Multicast Routing Protocol (DVMRP). Note that any maximum limits provided in the table are subject to available system resources.

	OS9900	OS6900	OS6860	OS6865	
RFCs Supported	1075—Distance Vector Multicast Routing Protocol, Version 1 4087—IP Tunnel MIB 2715—Interoperability Rules for Multicast Routing Protocols				
IETF Internet-Drafts Supported	draft-ietf-idmr-dvmrp-v3-09.txt - Distance Vector Multicast Routing Protocol, Version 3				
DVMRP version supported	DVMRPv3.255				
DVMRP attributes supported	Reverse Path Multicasting, Neighbor Discovery, Multicast Source Location, Route Report Messages, Distance metrics, Dependent Downstream Routers, Poison Reverse, Pruning, Grafting, DVMRP Tunnels				
DVMRP timers supported	Flash update interval, Graft retransmissions, Neighbor probe interval, Neighbor timeout, Prune lifetime, Prune retransmission, Route report interval, Route hold-down, Route expiration timeout				
Maximum number of interfaces	384 (Maximum 384 combined Multicast Interfaces between PIMv4, PIMv6 and DVMRP.)				
Multicast protocols per interface	1 (PIM and DVMRP cannot be enabled on the same interface.)				
<b>Notes:</b>					
DVMRP is not supported on the OS9900.					

# PIM Specifications

The following Specifications table contains information for the OmniSwitch implementation of the Protocol-Independent Multicast (PIM) routing protocol. Note that any maximum limits provided in the table are subject to available system resources.

	OS9900	OS6900	OS6860	OS6865	
RFCs Supported	2365—Administratively Scoped IP Multicast 4601—Protocol Independent Multicast-Sparse Mode (PIM-SM) Protocol Specification 4007—IPv6 Scoped IP Multicast 5060—Protocol Independent Multicast MIB 5132—IP Multicast MIB 3569—An Overview of Source-Specific Multicast (SSM) 3973—Protocol Independent Multicast-Dense Mode (PIM-DM) 5015 - Bidirectional Protocol Independent Multicast (BIDIR-PIM) 5059—Bootstrap Router (BSR) Mechanism for PIM 5240—Protocol Independent Multicast (PIM) Bootstrap Router MIB 2715—Interoperability Rules for Multicast Routing Protocols				
PIM-SM version supported	PIM-SMv2				
PIM attributes supported	Shared trees (also referred to as RP trees) Designated Routers (DRs) Designated Forwarders (DFs) Bootstrap Routers (BSRs) Candidate Bootstrap Routers (C-BSRs) Rendezvous Points (RPs) (applicable only for PIM-SM) Candidate Rendezvous Points (C-RPs)				
PIM timers supported	C-RP expiry, C-RP holdtime, C-RP advertisement, Join/Prune, Probe, Register suppression, Hello, Expiry, Assert, Neighbor liveness, DF Election Timer				
Maximum PIM interfaces	384 (Maximum 384 combined Multicast Interfaces between PIMv4, PIMv6 and DVMRP.) 100 (OS9900)				
Maximum Rendezvous Point (RP)	100				
Maximum Bootstrap Routers (BSRs)	1				
Multicast Protocols per Interface	1 (PIM and DVMRP cannot be enabled on the same IP interface)				
Reserved SSM IPv4 Address Ranges	232.0.0.0 to 232.255.255.255				
Reserved SSM IPv6 Address Ranges	FF3x::/32				
<b>Notes:</b>					



## MBR Specifications

The following Specifications table contains information for the OmniSwitch implementation of the multicast border router (MBR) functionality defined in the PIM-SM specification (RFC 4601). Note that any maximum limits provided in the table are subject to available system resources.

	OS9900	OS6900	OS6860	OS6865	
RFCs Supported	4601—Protocol Independent Multicast-Sparse Mode (PIM-SM) Protocol Specification 3973—Protocol Independent Multicast-Dense Mode (PIM-DM) 2715—Interoperability Rules for Multicast Routing Protocols				
IETF Internet-Drafts Supported	draft-ietf-idmr-dvmrp-v3-09.txt - Distance Vector Multicast Routing Protocol, Version 3				
MBR Interoperability	DVMRP interoperability with IPv4 PIM (PIM-SM and PIM-DM only).				
<b>Notes:</b>					

# 4 Data Center Switching Specifications

The OmniSwitch implementation of data center switching capabilities helps enterprises address the challenges and ongoing transformation of data center networks. This chapter provides Specifications tables for the following OmniSwitch data center switching applications:

- Data Center Bridging (DCB) protocols to convert Ethernet into a lossless transport to support a reliable storage area network fabric within the data center mesh.
- Shortest Path Bridging MAC (SPBM), including SPBM support of Provider Backbone Bridging (PBB) encapsulation and services.
- Virtual eXtensible Local Area Network (VXLAN) to transparently extend Layer 2 networks over a Layer 3 infrastructure.
- VXLAN Snooping to detect and identify VXLAN traffic on the network.
- Fibre Channel over Ethernet (FCoE) Initialization Protocol (FIP) snooping to ensure the security of an FCoE network.
- FCoE/FC gateway functionality to converge FC over Ethernet and FC-to-FC over Ethernet through an OmniSwitch gateway.
- Edge Virtual Bridging (EVB) for managing virtual machines created and managed on servers also running the EVB protocol..

---

**Note.** The maximum limit values provided in the Specifications tables included in this chapter are subject to available system resources.

---

For information about how to configure data center switching applications, refer to the *OmniSwitch AOS Release 8 Data Center Switching Guide*.

## In This Chapter

This chapter contains the following data center Specifications tables:

- [“Data Center Bridging Specifications” on page 4-3.](#)
- [“Shortest Path Bridging Specifications” on page 4-4.](#)
- [“VXLAN Specifications” on page 4-5.](#)
- [“VXLAN Snooping Specifications” on page 4-5.](#)
- [“FIP Snooping Specifications” on page 4-6.](#)
- [“FCoE/FC Gateway Specifications” on page 4-7.](#)
- [“Edge Virtual Bridging Specifications” on page 4-8.](#)

## Data Center Bridging Specifications

The following Specifications table contains information for the OmniSwitch implementation of Data Center Bridging (DCB). Note that any maximum limits provided in the table are subject to available system resources.

	OS9900	OS6900	OS6860	OS6865
OmniSwitch Software License	Data Center	Data Center	N/S	N/S
IEEE Standards Supported	802.1Qbb— <i>Priority-based Flow Control</i> 802.1Qaz D2.5— <i>Enhanced Transmission Selection</i> 802.1Qaz D2.5— <i>Data Center Bridging Exchange Converged Enhanced Ethernet DCBX v.1.01</i> 802.1Q-REV/D1.5— <i>Media Access Control (MAC) Bridges and Virtual Bridged Local Area Networks</i>		N/S	N/S
Maximum number of DCB profiles	128 profiles: <ul style="list-style-type: none"> <li>• Profiles 1–11 are predefined, with profile 8 serving as the default profile for all ports.</li> <li>• Profiles 12–128 are reserved for user-defined (custom) profiles.</li> </ul>		N/S	N/S
Maximum number of lossless queues (priorities)	N/S	110	N/S	N/S
DCB TLVs supported	ETS Configuration ETS Recommendation PFC Configuration Application Priority		N/S	N/S
Notes:				
- The OS9900 does not support DCB.				

## Shortest Path Bridging Specifications

The following Specifications table contains information for the OmniSwitch implementation of Shortest Path Bridging (SPB). Note that any maximum limits provided in the table are subject to available system resources.

	OS9900	OS6900	OS6860	OS6865
IEEE Standards Supported	802.1aq/D3.6: Draft February 10, 2011— <i>Virtual Bridged Local Area Networks-Amendment 9: Shortest Path Bridging</i> 802.1ah/D4.2: DRAFT March 26, 2008— <i>Virtual Bridged Local Area Networks-Amendment 6: Provider Backbone Bridging</i>			
IETF Internet-Drafts Supported	draft-ietf-isis-ieee-aq-05.txt— <i>ISIS Extensions Supporting IEEE 802.1aq Shortest Path Bridging</i> IETF draft— <i>IP/IPVPN services with IEEE 802.1aq SPBB networks</i> IETF draft— <i>IP/IPVPN services with IEEE 802.1aq SPB networks</i>			
SPB mode supported	SPBM (MAC-in-MAC)			
IP over SPBM	IPv4 (VPN-Lite and L3 VPN) VRF-to-ISID mapping (one-to-one, one-to-many)			
Maximum number of ISIS-SPB instances per switch.	1			
Maximum number of BVLANS per switch	16			
Number of equal cost tree (ECT) algorithm IDs supported.	16 (Can select any ID between 1 and 16 to assign to a BVLAN)			
Maximum number of service instance identifiers (I-SIDs) per switch	1K	N/S	1K Q32 - 8K X72 - 8K	2K  2K
Maximum number of VLANs or SVLANs per I-SID	4K	N/S	4K	2K  2K
Maximum number of SAPs	8K	N/S	X20 - 4K X40 - 4K T20 - 8K T40 - 8K Q32 - 8K X72 - 8K	2K  2K
Maximum Transmission Unit (MTU) size for SPB services.	9K (not configurable at this time)			
Maximum number of Remote Fault Propagation (RFP) domains.	8 (or less if there are other Ethernet OAM domains already configured on the switch)		N/S	N/S
<b>Notes:</b>				
- SPB is not supported on the OS9900. - In a VC with OS6900-X models, the maximum number of SAPs is 4K.				

## VXLAN Specifications

The following Specifications table contains information for the OmniSwitch implementation of the Virtual eXtensible LAN (VXLAN) feature. Note that any maximum limits provided in the table are subject to available system resources.

	OS6900
RFCs Supported	7348— <i>VXLAN: A Framework for Overlaying Layer 2 Virtualized Networks over Layer 3 Networks.</i>
VXLAN segments (L2 overlay networks)	16 million
VXLAN service instances	8K
VXLAN Tunnel End Points in a VXLAN network.	500
VXLAN UDP destination ports	8 (including the default UDP port number, which is 4789).
VXLAN Service Access Points (SAPs)	8K (per device or per Virtual Chassis)
VXLAN SAPs with a VLAN ID range	8 SAPs per service access port
Service access ports with SAPs that contain a VLAN ID range	255
VXLAN Network IDs (VNIs)	4K
Multicast Groups	500
Multicast protocol supported	Bidirectional PIM (BIDIR-PIM)
<b>Notes:</b>	
VXLAN is only supported on the OmniSwitch 6900-Q32 and OmniSwitch 6900-X72.	

## VXLAN Snooping Specifications

The following Specifications table contains information for the OmniSwitch implementation of VXLAN Snooping. Note that any maximum limits provided in the table are subject to available system resources.

	OS9900	OS6900	OS6860	OS6865
RFCs Supported	7348— <i>VXLAN: A Framework for Overlaying Layer 2 Virtualized Networks over Layer 3 Networks.</i>		N/S	N/S
Packet sampling rate	1K packets-per-second on each module.		N/S	N/S
<b>Notes:</b>				
- VXLAN Snooping is not supported on the OS9900.				

## FIP Snooping Specifications

The following Specifications table contains information for the OmniSwitch implementation of FIP Snooping and FCoE. Note that any maximum limits provided in the table are subject to available system resources.

	OS9900	OS6900	OS6860	OS6865
OmniSwitch Software License	Data Center	Data Center	N/S	N/S
INCITS Standards Supported	<ul style="list-style-type: none"> <li>• T11 Fibre Channel Backbone - 5 (FC-BB-5) Rev 2.00 June 4, 2009</li> <li>• FC-BB-5 Annex C: Increasing FC-BB_E Robustness Using Access Control Lists</li> <li>• T11 Switch Fabric - 5 (FC-SW-5) Rev 8.5 June 3, 2009</li> </ul>		N/S	N/S
Maximum number of FIP Snooping Sessions	128 Maximum number of FIP Snooping Sessions		N/S	N/S
Required port types	10G or faster Ethernet with DCB profile and DCBx enabled with PFC/ETS active (ports and link aggregates)		N/S	N/S
<b>Notes:</b>				
- FIP Snooping is not supported on the OS9900.				

# FCoE/FC Gateway Specifications

The following Specifications table contains information for the OmniSwitch FCoE/FC Gateway. Note that any maximum limits provided in the table are subject to available system resources.

	<b>OS6900</b>
OmniSwitch Software License	Data Center
INCITS Standards Supported	<ul style="list-style-type: none"> <li>• FC-PI-4 Fibre Channel T11/08-138v1</li> <li>• FC-PI-5 Fibre Channel T11 2118-D/Rev 6.10</li> <li>• FC-BB-5 Backbone 5 T11/1871-D</li> <li>• FC-BB-6 Backbone 6 T11/2159-D (CNA switching only)</li> </ul>
Fibre Channel functionality supported	<ul style="list-style-type: none"> <li>• FCoE transit bridge               <ul style="list-style-type: none"> <li>- FCoE tunneling of encapsulated FC frames</li> <li>- FCoE initialization protocol (FIP) snooping</li> </ul> </li> <li>• FCoE/FC gateway switch               <ul style="list-style-type: none"> <li>- N_Port proxy (NPIV)</li> <li>- F_Port proxy (Reverse-NPIV)</li> <li>- E_Port proxy (E2E-tunnel)</li> </ul> </li> </ul>
Supported port types	<ul style="list-style-type: none"> <li>• Fibre Channel for FCoE/FC gateway—OS-XNI-U12E module with SFP-FC-SR transceiver</li> <li>• Ethernet for FCoE/FIP snooping—10G or faster with DCB profile, DCBx enabled with PFC/ETS active (ports and link aggregates)</li> </ul>
OmniSwitch 64-bit World Wide Node Name (WWNN)	10:00:xx:xx:xx:xx:xx:xx (where xx = next available increment of the switch base MAC address)
OmniSwitch 64-bit World Wide Port Name (WWPN) for each Fibre Channel port	10:00:xx:xx:xx:xx:xx:xx (where xx = port MAC address)
VSAN–FC port associations	Multiple FC port assignments per VSAN allowed. Only one VSAN assignment per FC port allowed.
VSAN–FCoE VLAN mapping	One-to-one
VSAN scalability per switch	Based on the number of FC ports (for example, if switch has 12 FC ports, then 12 VSANs; one for each FC port). Note that an FC port configured as an E2E tunnel endpoint does not use up a VSAN assignment.
Maximum number of VSANs per network	4094
E2E tunnel scalability	One tunnel termination per FC port up to the number of available FC ports on the switch or virtual chassis.
Maximum frame size supported	2180
Load Balancing	NP_Port load balancing only: <ul style="list-style-type: none"> <li>• Dynamic</li> <li>• Dynamic-reorder</li> <li>• ENode-based</li> <li>• Static</li> </ul>
<b>Notes:</b>	
Only an OmniSwitch 6900 with the supported port types can serve as an FCoE/FC Gateway switch.	



## Edge Virtual Bridging Specifications

The following Specifications table contains information for the OmniSwitch implementation of Edge Virtual Bridging (EVB). Note that any maximum limits provided in the table are subject to available system resources.

	OS9900	OS6900	OS6860	OS6865
OmniSwitch Software License	Data Center	Data Center	N/S	N/S
IEEE Standards Supported	P802.1Qbg Standard Draft, Revision D2.2. February 18, 2012— <i>Virtual Bridged Local Area Networks—Amendment 21: Edge Virtual Bridging</i>		N/S	N/S
EVB mode	Bridging (virtual machines request the required CVLAN ID tag)		N/S	N/S
Edge Relay (ER) support	Single ER per switch port. The ER can operate as a Virtual Ethernet Port Aggregator (VEPA) or as a Virtual Ethernet Bridge (VEB).		N/S	N/S
<b>Notes:</b>				
- EVB is not supported on the OS9900.				

# A Software License and Copyright Statements

This appendix contains ALE USA, Inc. and third-party software vendor license and copyright statements.

## ALE USA, Inc. License Agreement

### ALE USA, Inc. SOFTWARE LICENSE AGREEMENT

---

**IMPORTANT.** Please read the terms and conditions of this license agreement carefully before opening this package.

---

**By opening this package, you accept and agree to the terms of this license agreement. If you are not willing to be bound by the terms of this license agreement, do not open this package. Please promptly return the product and any materials in unopened form to the place where you obtained it for a full refund.**

1. **License Grant.** This is a license, not a sales agreement, between you (the “Licensee”) and ALE USA, Inc.. ALE USA, Inc. hereby grants to Licensee, and Licensee accepts, a non-exclusive license to use program media and computer software contained therein (the “Licensed Files”) and the accompanying user documentation (collectively the “Licensed Materials”), only as authorized in this License Agreement. Licensee, subject to the terms of this License Agreement, may use one copy of the Licensed Files on the Licensee’s system. Licensee agrees not to assign, sublicense, transfer, pledge, lease, rent, or share their rights under this License Agreement. Licensee may retain the program media for backup purposes with retention of the copyright and other proprietary notices. Except as authorized under this paragraph, no copies of the Licensed Materials or any portions thereof may be made by Licensee and Licensee shall not modify, decompile, disassemble, reverse engineer, or otherwise attempt to derive the Source Code. Licensee is also advised that ALE USA, Inc. products contain embedded software known as firmware which resides in silicon. Licensee may not copy the firmware or transfer the firmware to another medium.

2. **ALE USA, Inc.’s Rights.** Licensee acknowledges and agrees that the Licensed Materials are the sole property of ALE USA, Inc. and its licensors (herein “its licensors”), protected by U.S. copyright law, trademark law, and are licensed on a right to use basis. Licensee further acknowledges and agrees that all rights, title, and interest in and to the Licensed Materials are and shall remain with ALE USA, Inc. and its licensors and that no such right, license, or interest shall be asserted with respect to such copyrights and trademarks. This License Agreement does not convey to Licensee an interest in or to the Licensed Materials, but only a limited right to use revocable in accordance with the terms of this License Agreement.

3. **Confidentiality.** ALE USA, Inc. considers the Licensed Files to contain valuable trade secrets of ALE USA, Inc., the unauthorized disclosure of which could cause irreparable harm to ALE USA, Inc.. Except as expressly set forth herein, Licensee agrees to use reasonable efforts not to disclose the Licensed Files to any third party and not to use the Licensed Files other than for the purpose authorized by this License Agreement. This confidentiality obligation shall continue after any termination of this License Agreement.

4. **Indemnity.** Licensee agrees to indemnify, defend and hold ALE USA, Inc. harmless from any claim, lawsuit, legal proceeding, settlement or judgment (including without limitation ALE USA, Inc.'s reasonable United States and local attorneys' and expert witnesses' fees and costs) arising out of or in connection with the unauthorized copying, marketing, performance or distribution of the Licensed Files.

5. **Limited Warranty.** ALE USA, Inc. warrants, for Licensee's benefit alone, that the program media shall, for a period of ninety (90) days from the date of commencement of this License Agreement (referred to as the Warranty Period), be free from defects in material and workmanship. ALE USA, Inc. further warrants, for Licensee benefit alone, that during the Warranty Period the Licensed Files shall operate substantially in accordance with the functional specifications in the User Guide. If during the Warranty Period, a defect in the Licensed Files appears, Licensee may return the Licensed Files to ALE USA, Inc. for either replacement or, if so elected by ALE USA, Inc., refund of amounts paid by Licensee under this License Agreement. EXCEPT FOR THE WARRANTIES SET FORTH ABOVE, THE LICENSED MATERIALS ARE LICENSED "AS IS" AND ALE USA, Inc. AND ITS LICENSORS DISCLAIM ANY AND ALL OTHER WARRANTIES, WHETHER EXPRESS OR IMPLIED, INCLUDING (WITHOUT LIMITATION) ANY IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. SOME STATES DO NOT ALLOW THE EXCLUSION OF IMPLIED WARRANTIES SO THE ABOVE EXCLUSIONS MAY NOT APPLY TO LICENSEE. THIS WARRANTY GIVES THE LICENSEE SPECIFIC LEGAL RIGHTS. LICENSEE MAY ALSO HAVE OTHER RIGHTS WHICH VARY FROM STATE TO STATE.

6. **Limitation of Liability.** ALE USA, Inc.'s cumulative liability to Licensee or any other party for any loss or damages resulting from any claims, demands, or actions arising out of or relating to this License Agreement shall not exceed the license fee paid to ALE USA, Inc. for the Licensed Materials. IN NO EVENT SHALL ALE USA, Inc. BE LIABLE FOR ANY INDIRECT, INCIDENTAL, CONSEQUENTIAL, SPECIAL, OR EXEMPLARY DAMAGES OR LOST PROFITS, EVEN IF ALE USA, Inc. HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. SOME STATES DO NOT ALLOW THE LIMITATION OR EXCLUSION OF LIABILITY FOR INCIDENTAL OR CONSEQUENTIAL DAMAGES, SO THE ABOVE LIMITATION OR EXCLUSION TO INCIDENTAL OR CONSEQUENTIAL DAMAGES MAY NOT APPLY TO LICENSEE.

7. **Export Control.** This product is subject to the jurisdiction of the United States. Licensee may not export or reexport the Licensed Files, without complying with all United States export laws and regulations, including but not limited to (i) obtaining prior authorization from the U.S. Department of Commerce if a validated export license is required, and (ii) obtaining "written assurances" from licensees, if required.

8. **Support and Maintenance.** Except as may be provided in a separate agreement between ALE USA, Inc. and Licensee, if any, ALE USA, Inc. is under no obligation to maintain or support the copies of the Licensed Files made and hereunder and ALE USA, Inc. has no obligation to furnish Licensee with any further assistance, documentation or information of any nature or kind.

9. **Term.** This License Agreement is effective upon Licensee opening this package and shall continue until terminated. Licensee may terminate this License Agreement at any time by returning the Licensed Materials and all copies thereof and extracts therefrom to ALE USA, Inc. and certifying to ALE USA, Inc. in writing that all Licensed Materials and all copies thereof and extracts therefrom have been returned or erased by the memory of Licensee's computer or made non-readable. ALE USA, Inc. may terminate this License Agreement upon the breach by Licensee of any term hereof. Upon such termination by ALE USA,

Inc., Licensee agrees to return to ALE USA, Inc. or destroy the Licensed Materials and all copies and portions thereof.

**10. Governing Law.** This License Agreement shall be construed and governed in accordance with the laws of the State of California.

**11. Severability.** Should any term of this License Agreement be declared void or unenforceable by any court of competent jurisdiction, such declaration shall have no effect on the remaining terms herein.

**12. No Waiver.** The failure of either party to enforce any rights granted hereunder or to take action against the other party in the event of any breach hereunder shall not be deemed a waiver by that party as to subsequent enforcement of rights or subsequent actions in the event of future breaches.

**13. Notes to United States Government Users.** Software and documentation are provided with restricted rights. Use, duplication or disclosure by the government is subject to (i) restrictions set forth in GSA ADP Schedule Contract with ALE USA, Inc.'s reseller(s), or (ii) restrictions set forth in subparagraph (c) (1) and (2) of 48 CFR 52.227-19, as applicable.

**14. Third Party Materials.** Licensee is notified that the Licensed Files contain third party software and materials licensed to ALE USA, Inc. by certain third party licensors. Some third party licensors are third part beneficiaries to this License Agreement with full rights of enforcement. Please refer to the section entitled "[Third Party Licenses and Notices](#)" on page -4 for the third party license and notice terms.

## Third Party Licenses and Notices

Legal Notices applicable to any software alone or in connection with the product to which this document pertains, are contained in files within the software itself located at: **/flash/foss**.

Also, if needed, we provide all FOSS (Free and Open Source Software) source code used into this release at the following URL: <https://support.esd.alcatel-lucent.com>.

# Index

USB Flash Drive 1-5

## U

USB Flash Drive  
specifications 1-5

## B

BGP  
specifications 3-5

## C

CMM  
specifications 1-5

## D

DVMRP  
specifications 3-6

## I

IS-IS  
specifications 3-4

## M

MBR  
specifications 3-8  
Multicast Address Boundary  
specifications 3-6

## O

OSPF  
specifications 3-2  
OSPFv3  
specifications 3-3

## P

PIM  
specifications 3-7

## S

SNMP  
specifications 1-7  
specifications  
BGP 3-5  
CMM 1-5  
DVMRP 3-6  
IS-IS 3-4  
MBR 3-8  
Multicast Address Boundary 3-6  
OSPF 3-2  
OSPFv3 3-3  
PIM 3-7  
SNMP 1-7