

Ruckus ICX 7250 Switch Technical Specifications

Copyright, Trademark and Proprietary Rights Information

© 2018 ARRIS Enterprises LLC. All rights reserved.

No part of this content may be reproduced in any form or by any means or used to make any derivative work (such as translation, transformation, or adaptation) without written permission from ARRIS International plc and/or its affiliates ("ARRIS"). ARRIS reserves the right to revise or change this content from time to time without obligation on the part of ARRIS to provide notification of such revision or change.

Export Restrictions

These products and associated technical data (in print or electronic form) may be subject to export control laws of the United States of America. It is your responsibility to determine the applicable regulations and to comply with them. The following notice is applicable for all products or technology subject to export control:

These items are controlled by the U.S. Government and authorized for export only to the country of ultimate destination for use by the ultimate consignee or end-user(s) herein identified. They may not be resold, transferred, or otherwise disposed of, to any other country or to any person other than the authorized ultimate consignee or end-user(s), either in their original form or after being incorporated into other items, without first obtaining approval from the U.S. government or as otherwise authorized by U.S. law and regulations.

Disclaimer

THIS CONTENT AND ASSOCIATED PRODUCTS OR SERVICES ("MATERIALS"), ARE PROVIDED "AS IS" AND WITHOUT WARRANTIES OF ANY KIND, WHETHER EXPRESS OR IMPLIED. TO THE FULLEST EXTENT PERMISSIBLE PURSUANT TO APPLICABLE LAW, ARRIS DISCLAIMS ALL WARRANTIES, EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, TITLE, NON-INFRINGEMENT, FREEDOM FROM COMPUTER VIRUS, AND WARRANTIES ARISING FROM COURSE OF DEALING OR COURSE OF PERFORMANCE. ARRIS does not represent or warrant that the functions described or contained in the Materials will be uninterrupted or error-free, that defects will be corrected, or are free of viruses or other harmful components. ARRIS does not make any warranties or representations regarding the use of the Materials in terms of their completeness, correctness, accuracy, adequacy, usefulness, timeliness, reliability or otherwise. As a condition of your use of the Materials, you warrant to ARRIS that you will not make use thereof for any purpose that is unlawful or prohibited by their associated terms of use.

Limitation of Liability

IN NO EVENT SHALL ARRIS, ARRIS AFFILIATES, OR THEIR OFFICERS, DIRECTORS, EMPLOYEES, AGENTS, SUPPLIERS, LICENSORS AND THIRD PARTY PARTNERS, BE LIABLE FOR ANY DIRECT, INDIRECT, SPECIAL, PUNITIVE, INCIDENTAL, EXEMPLARY OR CONSEQUENTIAL DAMAGES, OR ANY DAMAGES WHATSOEVER, EVEN IF ARRIS HAS BEEN PREVIOUSLY ADVISED OF THE POSSIBILITY OF SUCH DAMAGES, WHETHER IN AN ACTION UNDER CONTRACT, TORT, OR ANY OTHER THEORY ARISING FROM YOUR ACCESS TO, OR USE OF, THE MATERIALS. Because some jurisdictions do not allow limitations on how long an implied warranty lasts, or the exclusion or limitation of liability for consequential or incidental damages, some of the above limitations may not apply to you.

Trademarks

ARRIS, the ARRIS logo, Ruckus, Ruckus Wireless, Ruckus Networks, Ruckus logo, the Big Dog design, BeamFlex, ChannelFly, EdgIron, FastIron, HyperEdge, ICX, IronPoint, OPENG, SmartCell, Unleashed, Xclaim, ZoneFlex are trademarks of ARRIS International plc and/or its affiliates. Wi-Fi Alliance, Wi-Fi, the Wi-Fi logo, the Wi-Fi CERTIFIED logo, Wi-Fi Protected Access (WPA), the Wi-Fi Protected Setup logo, and WMM are registered trademarks of Wi-Fi Alliance. Wi-Fi Protected Setup™, Wi-Fi Multimedia™, and WPA2™ are trademarks of Wi-Fi Alliance. All other trademarks are the property of their respective owners.

Contents

Ruckus ICX 7250 Switch Technical Specifications.....	5
System specifications.....	5
Ethernet.....	5
LEDs.....	6
Other.....	6
Weight and physical dimensions.....	6
Environmental requirements.....	7
Power supply specifications (per PSU).....	7
Power consumption (idle configuration).....	8
Power consumption (typical configuration).....	9
Power consumption (maximum configuration).....	9
Data port specifications (Ethernet).....	10
Serial port specifications (pinout mini-USB).....	11
Serial port specifications (protocol).....	11
Memory specifications.....	11
Regulatory compliance (EMC).....	11
Regulatory compliance (safety).....	12
Regulatory compliance (environmental).....	12

Ruckus ICX 7250 Switch Technical Specifications

This content highlights the features and specifications for the Ruckus ICX 7250 switch.

System specifications

System component	Description
Enclosure	1U; 19-inch rack-mountable; desktop- or wall-mountable
Power inlet	C14 for AC power Custom connector for DC power from EPS4000 (not available on the ICX 7250-24G)
Power supplies	Integrated AC power supply for system and PoE power External AC power supply (EPS4000) for redundant system power and extended PoE/PoE+ power (not applicable to the ICX 7250-24G). DC power supplied to the switches depends on the EPS4000 configuration.
Fans	ICX 7250-24G: One fan per device ICX 7250-24 : One fan per device ICX 7250-24P: Two fans per device ICX 7250-48: Two fans per device ICX 7250-48P: Three fans per device
Cooling	Forced air circulation ICX 7250-24G: front-to-back airflow All other models: sides-to-back airflow
System architecture	Edge Ethernet switches ICX 7250-24G: SFP uplink ports ICX 7250-24, ICX 7250-24P, ICX 7250-48, ICX 7250-48P: SFP+ uplink and stacking ports ICX 7250-24P, ICX 7250-48P: PoE/PoE+ ports

Ethernet

System component	Description
Ethernet ports	ICX 7250-24G: 24 RJ-45 GbE, 4 SFP GbE ICX 7250-24: 24 RJ-45 GbE, 8 SFP+ 10 GbE ICX 7250-24P: 24 RJ-45 GbE with PoE/PoE+, 8 SFP+ 10 GbE ICX 7250-48: 48 RJ-45 GbE, 8 SFP+ 10 GbE ICX 7250-48P: 48 RJ-45 GbE with PoE/PoE+, 8 SFP+ 10 GbE
Management interface	One 10/100/1000 Ethernet, out-of-band management interface (RJ-45 port)

LEDs

System component	Description
Port status LEDs	<p>RJ-45: Indicates Ethernet link status and speed</p> <p>PoE/PoE+: Indicates if a port is providing PoE or PoE+ power to a connected device</p> <p>SFP/SFP+: Indicates link status and speed for SFP or SFP+ ports</p> <p>Out-of-band management port: Two single-color LEDs indicate out-of-band management port link status and speed</p>
System status LEDs	<p>PWR: Bicolor LED (green/amber) indicates the internal power status</p> <p>DIAG: Bicolor LED (green/amber) controlled by software to indicate the system is in diagnostic mode</p> <p>NOTE The following LEDs are not available on the ICX 7250-24G.</p> <p>EPS1: Bicolor LED (green/amber) indicates if the external power supply (EPS1) is operating normally</p> <p>EPS2 (available only on the ICX 7250-48P): Bicolor LED (green/amber) indicates if the external power supply (EPS2) is operating normally</p> <p>MS: Bicolor LED (green/amber) controlled by software to indicate master/slave status in stacking mode</p> <p>UPLINK: Software-controlled LED (green) to indicate stacking uplink port status</p> <p>DOWNLINK: Software-controlled LED (green) to indicate stacking uplink port status</p> <p>(Stack) ID: Ten LEDs (green) to display stacking ID from 1 to 19. The LED marked 10+ is used in conjunction with the others (1 through 9) to indicate stacking IDs 11 to 19.</p> <p>NOTE For those devices that support stacking, the maximum stack size is 12 units.</p>

Other

System component	Description
RESET	Reset button for hardware reset without power cycling. There is a hole in the front panel to allow access.
Mini-USB port	Console port for serial access to the device for management
USB port	Standard type-A USB connector for removable media
Serial cable	Mini-USB to RJ-45 console cable: BPN 50-1000122-01
RJ-45 connector	2x6 stacked RJ-45 connectors for GbE data ports

Weight and physical dimensions

Model	Height	Width	Depth	Weight
ICX 7250-24G	4.37 cm	44.0 cm	28 cm	3.6 kg
	1.72 in	17.32 in	11 in	7.9 lb
ICX 7250-24	4.37 cm	44.0 cm	28 cm	3.8 kg
	1.72 in	17.32 in	11 in	8.4 lb
ICX 7250-24P	4.37 cm	44.0 cm	28 cm	4.7 kg

Model	Height	Width	Depth	Weight
	1.72 in	17.32 in	11 in	10.3 lb
ICX 7250-48	4.37 cm	44.0 cm	37 cm	4.8 kg
	1.72 in	17.32 in	14.6 in	10.6 lb
ICX 7250-48P	4.37 cm	44.0 cm	37 cm	5.9 kg
	1.72 in	17.32 in	14.6 in	13.0 lb

Environmental requirements

Condition	Operational	Non-operational
Ambient temperature	-5°C to 50°C (23°F to 122°F)	-25°C to 70°C (-13°F to 158°F)
Relative humidity (non-condensing)	5% to 95% at 50°C (122°F)	5% to 95% at 70°C (158°F)
Altitude (above sea level)	0 to 3,000 m (10,000 feet)	0 to 12,000 m (39,000 feet)
Shock	20 G, 11 ms, half-sine wave	33 G, 11 ms, half-sine wave
Vibration	1 G sine, 0.4 gms random, 5-500 Hz	2.4 G sine, 1.1 gms random, 5-500 Hz
Airflow	ICX 7250-24G: 14.3 CFM (Maximum), 5.7 CFM (Typical) ICX 7250-24 : 14.0 CFM (Maximum), 5.7 CFM (Typical) ICX 7250-24P: 34.4 CFM (Maximum), 13.7 CFM (Typical) ICX 7250-48: 34.8 CFM (Maximum), 13.8 CFM (Typical) ICX 7250-48P: 45.2 CFM (Maximum), 21.4 CFM (Typical)	N/A
Heat dissipation	Refer to Power Consumption specification sections	N/A
Operating noise	ICX 7250-24G: 40 dBA ICX 7250-24: 41.9 dBA ICX 7250-24P: 44.7 dBA ICX 7250-48: 44.5 dBA ICX 7250-48P: 45.9 dBA	N/A

Power supply specifications (per PSU)

The EPS4000 and its power supply modules (RPS17) are field-replaceable. All other Ruckus ICX 7250 power supply units (PSUs) are fixed and internal to the devices. All the PSUs use a C14 inlet and connect to standard AC power.

NOTE

The EPS4000 must have at least one RPS17 installed to provide power to the supported Ruckus ICX 7250 devices.

Device	Maximum output power rating (DC)	Input voltage	Input line frequency	Maximum input current	Input line protection	Maximum inrush current
ICX 7250-24G	65 W	100 - 240 VAC	50/60 Hz	1.5 A (rms)	Line fused	40 A at 115 VAC
ICX 7250-24		(nominal) 90 - 264 VAC (range)	(nominal) 47 - 63 Hz (range)			80 A at 230 VAC Cold start @ 25°C

Ruckus ICX 7250 Switch Technical Specifications
Power consumption (idle configuration)

Device	Maximum output power rating (DC)	Input voltage	Input line frequency	Maximum input current	Input line protection	Maximum inrush current
ICX 7250-24P	525 W	100 - 240 VAC (nominal) 90 - 264 VAC (range)	50/60 Hz (nominal) 47 - 63 Hz (range)	6 A (rms)	Line fused	30 A at 115 VAC 60 A at 230 VAC Cold start @ 25°C
ICX 7250-48	100 W	100 - 240 VAC (nominal) 90 - 264 VAC (range)	50/60 Hz (nominal) 47 - 63 Hz (range)	2.0 A (rms)	Line fused	65 A at 115 VAC 130 A at 230 VAC Cold start @ 25°C
ICX 7250-48P	880 W	100 - 240 VAC (nominal) 90 - 264 VAC (range)	50/60 Hz (nominal) 47 - 63 Hz (range)	10.8 A (rms)	Line and neutral fused	60 A at 115 VAC 120 A at 230 VAC Cold start @ 25°C
EPS4000	920 W (per installed PSU)	100 - 240 VAC (nominal) 90 - 264 VAC (range)	50/60 Hz (nominal) 47 - 63 Hz (range)	13 A (rms)	Line and neutral fused	75 A at 230 VAC Cold start @ 25°C

Power consumption (idle configuration)

Idle: No optics or connections to ports installed and system booted up. Fans at nominal speed.

NOTE

The Ruckus ICX 7250 does not support -48 VDC input power.

Model name	@100 VAC input	@200 VAC input	@-48 VDC input	Minimum number of power supplies	Notes
ICX 7250-24G	0.56 A 33.6 W 114.7 BTU/hr	0.35 A 33.3 W 113.5 BTU/hr	N/A	1	All ports down, no optics or cables connected. No Load (traffic)
ICX 7250-24	0.71 A 42.6 W 145.4 BTU/hr	0.41 A 39.0 W 132.9 BTU/hr	N/A	1	All ports down, no optics or cables connected. No Load (traffic)
ICX 7250-24P	0.5 A 48.0 W 163.8 BTU/hr	0.36 A 48.0 W 163.8 BTU/hr	N/A	1	All ports down, no optics or cables connected. No Load (traffic)
ICX 7250-48	0.51 A 50.6 W 172.8 BTU/hr	0.28 A 51.1 W 174.3 BTU/hr	N/A	1	All ports down, no optics or cables connected. No Load (traffic)

Model name	@100 VAC input	@200 VAC input	@-48 VDC input	Minimum number of power supplies	Notes
ICX 7250-48P	0.73 A 70.8 W 241.6 BTU/hr	0.46 A 70.8 W 241.6 BTU/hr	N/A	1	All ports down, no optics or cables connected. No Load (traffic)

Power consumption (typical configuration)

Typical: 10% traffic rate on all ports with 64-byte packet size and random payload at room temperature. All ports fully configured. Fans at nominal speed.

NOTE

The Ruckus ICX 7250 does not support -48 VDC input power.

Model name	@100 VAC input	@200 VAC input	@-48 VDC input	Minimum number of power supplies	Notes
ICX 7250-24G	0.71 A 42.6 W 216.9 BTU/hr	0.42 A 39.9 W 136.2 BTU/hr	N/A	1	24 1-GbE and 4 10-GbE ports are linked UP ONLY. 10% traffic.
ICX 7250-24	0.86 A 51.6 W 176.1 BTU/hr	0.52 A 49.4 W 168.6 BTU/hr	N/A	1	24 1-GbE and 8 10-GbE ports are linked UP ONLY. 10% traffic.
ICX 7250-24P	4.46 A 441.0 W 1505.2 BTU/hr	2.18 A 428.0 W 1460.8 BTU/hr	N/A	1	24 1-GbE and 8 10-GbE ports are linked UP ONLY. 10% traffic. 100% PoE Load @ Class 3 (15.4 W/port)
ICX 7250-48	0.64 A 63.6 W 216.9 BTU/hr	0.34 A 61.1 W 208.6 BTU/hr	N/A	1	48 1-GbE and 8 10-GbE ports are linked UP ONLY. 10% traffic.
ICX 7250-48P	9.23 A 920.0 W 3140.0 BTU/hr	4.43 A 862.0 W 2942.1 BTU/hr	N/A	1	48 1-GbE and 8 10-GbE ports are linked UP ONLY. 10% traffic. 100% PoE Load @ Class 3 (15.4 W/port)

Power consumption (maximum configuration)

Maximum: All ports fully configured with connection and traffic at maximum throughput. Fans at high speed.

NOTE

The Ruckus ICX 7250 does not support -48 VDC input power.

Model name	@100 VAC input	@200 VAC input	@-48 VDC input	Minimum number of power supplies	Notes
ICX 7250-24G	0.74 A 44.4 W 151.5 BTU/hr	0.45 A 42.3 W 144.3 BTU/hr	N/A	1	24 1-GbE and 4 10-GbE ports are linked UP ONLY. 100% traffic.
ICX 7250-24	0.96 A 57.6 W 196.6 BTU/hr	0.57 A 54.2 W 184.8 BTU/hr	N/A	1	24 1-GbE and 8 10-GbE ports are linked UP ONLY. 100% traffic.
ICX 7250-24P	4.56 A 454.0 W 1549.5 BTU/hr	2.24 A 439.0 W 1498.3 BTU/hr	N/A	1	24 1-GbE and 8 10-GbE ports are linked UP ONLY. 100% traffic. 100% PoE Load @ Class 3 (15.4 W/port)
ICX 7250-48	0.70 A 69.5 W 237.2 BTU/hr	0.38 A 69.3 W 236.6 BTU/hr	N/A	1	48 1-GbE and 8 10-GbE ports are linked UP ONLY. 10% traffic.
ICX 7250-48P	9.45 A 942.0 W 3215.1 BTU/hr	4.49 A 880.0 W 3003.5 BTU/hr	N/A	1	48 1-GbE and 8 10-GbE ports are linked UP ONLY. 10% traffic. 100% PoE Load @ Class 3 (15.4 W/port)

Data port specifications (Ethernet)

NOTE

The ICX 7250 10G ports provide a combination of active and passive cable support. Ports 1/2/1 to 1/2/4 can only be used with active cables when used for uplinks and either passive or active when used for stacking. Ports 1/2/5 to 1/2/8 can be used with either active or passive cable for any connection type.

Model	Port type	Number of ports	Description
ICX 7250-24G	GbE (copper)	24	RJ-45 10/100/1000 ports
	GbE (optical)	4	SFP uplink ports
ICX 7250-24	GbE (copper)	24	RJ-45 10/100/1000 ports
	10 GbE (optical)	8	Uplink or stacking SFP+ ports
ICX 7250-24P	GbE (copper)	24	RJ-45 10/100/1000 ports
	10 GbE (optical)	8	Uplink or stacking SFP+ ports
ICX 7250-48	GbE (copper)	48	RJ-45 10/100/1000 ports
	10 GbE (optical)	8	Uplink or stacking SFP+ ports
ICX 7250-48P	GbE (copper)	48	RJ-45 10/100/1000 ports

Model	Port type	Number of ports	Description
	10 GbE (optical)	8	Uplink or stacking SFP+ ports

Serial port specifications (pinout mini-USB)

Pin	Signal	Description
1	Reserved	Not used
2	UART_RX	Receive data by Ruckus ICX 7250
3	UART_TX	Transmit data by Ruckus ICX 7250
4	Reserved	Not used
5	GND	Logic ground

Serial port specifications (protocol)

Parameter	Value
Baud	9600 bps
Data bits	8
Parity	None
Stop bits	1
Flow control	None

Memory specifications

Memory	Type	Size
Boot	SPI Flash	2 x 8 MB
Compact Flash	NAND	2 GB
Main	DDR3 (onboard IC)	ICX 7250-24G: 1 GB ICX 7250-24: 2 GB ICX 7250-24P: 2 GB ICX 7250-48: 2 GB ICX 7250-48P: 2 GB

Regulatory compliance (EMC)

- FCC Part 15, Subpart B (Class A)
- EN 55022 (CE mark) (Class A)
- EN 55024 (CE mark) (Immunity) for Information Technology Equipment
- ICES-003 (Canada) (Class A)
- AS/NZ 55022 (Australia) (Class A)

- VCCI (Japan) (Class A)
- EN 61000-3-2
- EN 61000-3-3
- EN 61000-6-1

Regulatory compliance (safety)

- CAN/CSA-C22.2 No. 60950/UL 60950
- EN 60825 Safety of Laser Products
- EN 60950/IEC 60950 Safety of Information Technology Equipment

Regulatory compliance (environmental)

- 2011/65/EU - Restriction of the use of certain hazardous substance in electrical and electronic equipment (EU RoHS).
- 2012/19/EU - Waste electrical and electronic equipment (EU WEEE).
- 94/62/EC - packaging and packaging waste (EU).
- 2006/66/EC - batteries and accumulators and waste batteries and accumulators (EU battery directive).
- 1907/2006 of the European Parliament and of the Council of 18 December 2006 concerning the Registration, Evaluation, Authorisation and Restriction of Chemicals (EU REACH).
- Section 1502 of the Dodd-Frank Wall Street Reform and Consumer Protection Act of 2010 - U.S. Conflict Minerals.
- 30/2011/TT-BCT - Vietnam circular.
- SJ/T 11363-2006 Requirements for Concentration Limits for Certain Hazardous Substances in EIPs (China).
- SJ/T 11364-2006 Marking for the Control of Pollution Caused by EIPs (China).



© 2018 ARRIS Enterprises LLC. All rights reserved.
Ruckus Wireless, Inc., a wholly owned subsidiary of ARRIS International plc.
350 West Java Dr., Sunnyvale, CA 94089 USA
www.ruckuswireless.com